

UNIVERSAL METER UT-51 UNI-TNet: **27.31 EUR** Gross: **27.31 EUR**

The UT-51 is universal digital multimeter designed to measurement of:
voltage, current, resistance, hFE, diodes.

SPECIFICATION

DC voltage measurement:	200 mV \pm (0.5% + 1) @ 0.1 mV , 2 V \pm (0.5% + 1) @ 0.001 V , 20 V \pm (0.5% + 1) @ 0.01 V , 200 V \pm (0.5% + 1) @ 0.1 V , 1000 V \pm (0.8% + 2) @ 1 V
AC voltage measurement:	200 mV \pm (1.2% + 3) @ 0.1 mV , 2 V \pm (0.8% + 3) @ 0.001 V , 20 V \pm (0.8% + 3) @ 0.01 V , 200 V \pm (0.8% + 3) @ 0.1 V , 750 V \pm (1.2% + 3) @ 1 V
DC current measurement:	20 μ A \pm (2.0% + 5) @ 0.01 μ A , 200 μ A \pm (0.8% + 1) @ 0.1 μ A , 2 mA \pm (0.8% + 1) @ 0.001 mA , 20 mA \pm (0.8% + 1) @ 0.01 mA , 200 mA \pm (1.5% + 1) @ 0.1 mA , 2 A \pm (1.5% + 1) @ 0.001 A , 10 A \pm (2.0% + 5) @ 0.01 A
AC current measurement:	200 μ A \pm (1.8% + 3) @ 0.1 μ A , 2 mA \pm (1.0% + 3) @ 0.001 mA , 20 mA \pm (1.0% + 3) @ 0.01 mA , 200 mA \pm (1.8% + 3) @ 0.1 mA , 2 A \pm (1.8% + 3) @ 0.001 A , 10 A \pm (3.0% + 7) @ 0.01 A

Resistance measurement:	200 Ω \pm (0.8% + 3) @ 0.1 Ω , 2 k Ω \pm (0.8% + 1) @ 0.001 k Ω , 20 k Ω \pm (0.8% + 1) @ 0.01 k Ω , 200 k Ω \pm (0.8% + 1) @ 0.1 k Ω , 2 M Ω \pm (0.8% + 1) @ 0.001 M Ω , 20 M Ω \pm (1.0% + 2) @ 0.01 M Ω , 200 M Ω \pm (5%(RD-10) + 10) @ 0.1 M Ω * *RD - reading value
Capacitance measurement:	—
Inductance measurement:	—
Frequency measurement:	—
Temperature measurement:	—
Automatic change of measuring ranges:	—
hFE:	✓
Diode test:	✓
Sound signal of the continuity test:	✓
Checking TTL logic states:	—
RS-232:	—
Main features:	<ul style="list-style-type: none"> • Large, readable LCD display • Low battery level alarm • Aesthetic and solid construction
Power supply:	9V, type 6F22 battery - included
Weight:	0.5 kg
Dimensions:	203 x 98 x 56 mm
Manufacturer / Brand:	UNI-T
Guarantee:	2 years

PRESENTATION

Front panel:



Rear view:



The device is equipped with a height-adjustable support:



Place for 9V battery:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------