



User Manual

Code: UR2-WE
WIRELESS SYSTEM CONTROL **UR2-WE** PYRONIX

Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order.

If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity;
2. Improper results of operation of the product or products related with it;
3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

The UR2-WE controller allows to use wireless detectors and Pyronix Enforcer remote controls in any alarm system. The device has 2 independent wireless channels, each of which controls a separate relay output.

Each wireless channel can be assigned to support wireless sensors (up to 10 per wireless channel) or remote controls (up to 6 per wireless channel). It is not possible to connect remote controls and detectors on one wireless channel.

Full bi-directional communication between the controller and the detectors allows an immediate reaction of the system in the event of a detector violation or an attempt to disrupt communication. In addition, the device has a separate FAULT relay, which is used to signal the sabotage of the device itself, detectors connected to it, low battery of the detector, attempts to disturb the radio signal, etc.



Support:	Pyronix Enforcer wireless detectors and remote controls
Number of supported wireless devices:	max. 20 - max. 6 remote controls / Wireless channel or max. 10 detectors / Wireless channel
Frequency band:	868 MHz
Range:	≤ 1600 m - in open area
Inputs:	1 pcs 0 V / 12 V
Relay outputs:	3 x 3 A @ 30 V DC (Lines 1, 2 + FAULT)
Main features:	<ul style="list-style-type: none"> • Bi-directional encrypted radio communication • The wireless channel can be assigned to support detectors or remote controls • Separate input responsible for controlling the arming of the alarm control panel (12V ARM or 0V ARM) • Adjustment of the duration of the relay output status change (3s / 60s) • Test mode • Quick pairing of the detector with the controller with a single button • Measurement of signal strength and quality • Tamper signaling
Power supply:	9 ... 15 V DC
Current consumption:	max. 80 mA
Operation temp:	-10 °C ... 50 °C
Weight:	0.26 kg
Dimensions:	174 x 126 x 32 mm

Manufacturer / Brand:	PYRONIX
SAP Code:	361300029
Guarantee:	2 years

Front panel:



Rear view:



Internal view of the housing:





User Manual

Code: UR2-WE
WIRELESS SYSTEM CONTROL **UR2-WE** PYRONIX

PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------