# Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.
Only persons who read the user manual may use the device.
The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.
The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order.
If the product has defects, it should not be used until it is repaired.
The product is intended for use at home and commercial use and may not be used for other than intended use.
The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.
The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:
1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity;
2. Improper results of operation of the product or products related with it;
3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

**Safety measures:**
Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.
The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.
**Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.**
Turn off the device before transporting it.
Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

**Proper product disposal:**
A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.
To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

# User Manual

Code: GT-CI31C5-28Z

IP CAMERA **GT-CI31C5-28Z** - 3.0 Mpx 2.8 ... 12 mm, MOTOZOOM GEMINI TECHNOLOGY

IP camera with efficient H.264 image compression algorithm for clear and smooth video streaming at maximal resolution of 2048 x 1536 (3.0 MPx).
The used motozoom lens with 2.8 ... 12 mm focal length allows to remote view angle adjustment. PoE powering possibility, compatible with the 802.3af standard makes the device more universal and easier to install.

| | |
|---|---|
| Standard: | TCP/IP, PAL |
| Sensor: | 1/2.8 " Sony CMOS IMX123 |
| Digital Image Processor: | Hisilicon 3516D |
| Matrix size: | 3.2 Mpx |
| Resolution: | 2048 x 1536 - 3.0 Mpx ,<br>1920 x 1080 - 1080p ,<br>1280 x 960 - 1.3 Mpx ,<br>1280 x 720 - 720p ,<br>704 x 576 - D1 |
| Lens: | 2.8 ... 12 mm, P-Iris, Motozoom |
| View angle: | • 88 ° ... 25 ° (manufacturer data)<br>• 80 ° ... 30 ° (our tests result) |
| S/N ratio: | > 50 dB |
| Range of IR illumination: | 50 m |
| IR illuminator power adjustment: | By potentiometer |
| Image compression method: | H.265 / H.264 / MJPEG |
| Alarm inputs / outputs: | — |
| Bitrate: | 16 ... 8000 kbps |
| Video output: | 1 Vpp / 75 Ω |
| Main stream frame rate: | max. 25 fps - 3.0 Mpx |
| Audio: | — |

DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

| | |
|---|---|
| Network interface: | 10/100 Base-T (RJ-45) |
| Network protocols: | TCP/IP, UDP, HTTP, DHCP, RTP/RTSP, DNS, DDNS, NTP, PPPOE, UPNP, SMTP |
| Mobile phones support: | Port no.: 5800 or access by a cloud (P2P)<br>• Android: Free application Fseye<br>• iOS: Free application Fseye |
| Default admin user / password: | admin / (null) |
| Default IP address: | 192.168.1.188 |
| Web browser access ports: | 80, 554, 1935 - Firmware V1.0, V1.1<br>80, 5050, 5051, 5052 - Firmware V4.0 - V4.3 |
| PC client access ports: | 5050, 5051, 5052 |
| WEB Server: | Built-in |
| Mobile client access ports: | 5800 |
| Max. number of on-line users: | 10 |
| Port ONVIF: | 80 - Firmware V1.0, V1.1<br>8000 - Firmware V4.0 - V4.3 |
| ONVIF: | 2.21 |
| RTSP URL: | rtsp://ip_address:554/ch01.264 - Main stream<br>rtsp://ip_address:554/ch01_sub.264 - Sub stream |
| RS-485 interface: | — |
| Main features: | • Motozoom lens<br>• ICR - Movable InfraRed filter<br>• 3D-DNR - Digital Noise Reduction<br>• WDR - Wide Dynamic Range<br>• Intelligent Video Analysis - abandoned, missing object detection, crossing the area or line detection<br>• Possibility to change the resolution, quality and bit rate<br>• Time mark and image description<br>• Image rotation and mirror<br>• Configurable: brightness, contrast, saturation<br>• Sharpness - sharper image outlines<br>• Day/Night mode - configurable<br>• Possibility to add different privileges to the users<br>• Privacy zones - max. 4 |
| Power consumption: | ≤ 7,7 W |
| Color: | Dark graphite |
| "Index of Protection": | IP65 |
| Power supply: | • PoE (802.3af),<br>• 12 V DC / 640 mA |
| Housing: | Compact, Metal |
| Supported languages: | English, Polish |
| Operation temp: | -20 °C ... 60 °C |
| Manufacturer / Brand: | GEMINI TECHNOLOGY |
| Weight: | 0.872 kg |


DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

| | |
|---|---|
| Dimensions: | 255 x 124 x 92 mm |
| Guarantee: | 2 years |

Front view:

Side view:

At the bottom of the camera has an openable cover under which is hidden IR illuminator adjustment and extra video output:



If you need to make an adjustment and open the cover, please follow the steps in the following order:
1 - loosen the Phillips screws (hinge),
2 - unscrew the Allen screws (cover),
3 - open the cover, make the adjustment and close the cover,
4 - screw the Allen screws (cover),
5 - tighten the Phillips screws (hinge).
This ensures the correct sealing pressure and tightness of the camera.
Mounting dimensions:




In the kit:

Package:

PACKAGE

| | |
|---|---|
| Dimensions (L x W x H): 0x0x0 mm | Gross Weight: 0 kg |

DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60