

Code: RB-33C

UNIVERSAL METER **RB-33C** REBEL Tools

Net: **108.02 NOK** Gross: **108.02 NOK**

RB-33C is a universal digital meter used to measure: voltage, current, resistance, temperature, diodes.

The kit includes a thermocouple of type "K" (chromel/alumel).



SPECIFICATION

DC voltage measurement:	200 mV $\pm$ (0.5% + 3) @ 0.1 mV , 2000 mV $\pm$ (0.8% + 5) @ 1 mV , 20 V $\pm$ (0.8% + 5) @ 0.01 V , 200 V $\pm$ (0.8% + 5) @ 0.1 V , 500 V $\pm$ (1.0% + 5) @ 1 V
AC voltage measurement:	200 V $\pm$ (2.0% + 10) @ 0.1 V , 500 V $\pm$ (2.0% + 10) @ 1 V
DC current measurement:	200 μ A $\pm$ (1.8% + 2) @ 0.1 μ A , 2000 μ A $\pm$ (1.8% + 2) @ 1 μ A , 20 mA $\pm$ (1.8% + 2) @ 0.01 mA , 200 mA $\pm$ (2.0% + 2) @ 0.1 mA , 10 A $\pm$ (2.0% + 10) @ 0.01 A
AC current measurement:	—
Resistance measurement:	200 Ω $\pm$ (1.0% + 10) @ 0.1 Ω , 2000 Ω $\pm$ (1.0% + 4) @ 1 Ω , 20 k Ω $\pm$ (1.0% + 4) @ 0.01 k Ω , 200 k Ω $\pm$ (1.0% + 4) @ 0.1 k Ω , 20 M Ω $\pm$ (1.0% + 10) @ 0.001 M Ω
Capacitance measurement:	—
Inductance measurement:	—
Frequency measurement:	—
Square-wave signal duty ratio measurement:	—

Temperature measurement:	• °C : -40 ... 150 °C ± (1.0% + 4) @ 1 °C , >150 ... 1370 °C ± (1.5% + 15) @ 1 °C • °F : -40 ... 302 °F ± (1.0% + 4) @ 1 °F , 302 ... 1999 °F ± (1.5% + 15) @ 1 °F
Automatic change of measuring ranges:	—
hFE:	—
Diode test:	✓
Sound signal of the continuity test:	✓
Checking TTL logic states:	—
RS-232:	—
Main features:	• Large, readable LCD display with backlight, • Aesthetic and solid construction, • Low battery level alarm
Power supply:	9V, type 6F22 battery - included
Weight:	0.17 kg
Dimensions:	134 x 77 x 36 mm
Manufacturer / Brand:	REBEL Tools
Guarantee:	2 years

PRESENTATION

Front panel:



Rear view:



Place for 9V battery:



In the kit:



PACKAGE

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
 POL; 60-713 Poznań; Graniczna 10
 e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------

