

Code: KD-185

INVERTER POWER GENERATOR **KD-185** 1500 W Kraft&Dele

Net: **639.96 EUR** Gross: **639.96 EUR**

The use of technology with the use of an inverter allows to obtain a stable output voltage that allows for safe powering of electronic receivers.

The inverter generator is used for emergency power supply, e.g. computers, server rooms, telephones, central heating furnace controllers, digitally controlled household equipment, heat pumps, electrically opened gates and garage gates, various medical devices and other devices sensitive to voltage fluctuations. It is also a convenient power supply in the field of tourism, e.g. caravans, campervans, boats, etc.

The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.



SPECIFICATION

Nominal power:	1500 W
Output voltage:	230 V AC
Number of outlets:	1 pcs - single-phase
Built-in voltmeter:	—
Output frequency:	50 Hz
Voltage stabilization:	Inverter (provides full voltage stabilization)
12V DC output:	✓
Engine capacity:	60 cm ³
Engine type:	R60-i 1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	≤ 95 dBA
Average fuel consumption:	min. 0.65 l/h
Fuel tank capacity:	2.6 l
Fuel gauge:	—

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Main features:	<ul style="list-style-type: none"> • Low oil level indicator light • Overload signaling • Overload protection • Battery charging possible • Save fuel by automatically reducing the revs as the load decreases • Possibility to combine two KD-185 power generators into one generator set
Color:	Yellow + Black
Weight:	13.7 kg
Dimensions:	420 x 240 x 385 mm
Manufacturer / Brand:	Kraft&Dele
Guarantee:	12 months

PRESENTATION

Front panel:





DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



The engine is started manually with a recoil starter:





Internal view of the housing:



Oil filler:



Fuel filler and access to spark plug:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------