



	ACCESS CONTROLLER PR621 ROGER	NVR BCS-B-NVR0801-8P(2.0) 8 CHANNELS, 8 PoE BCS BASIC
		
	806.31 DKK 806.31 DKK	1023.74 DKK 1023.74 DKK
Standard	...	TCP/IP
Relay contacts load	1.5 A / 30 V	...
Battery backup support	—	...
Supported resolutions	...	max. 8 Mpx 4K UHD - 3840 x 2160 px
Keyboard built-in	—	...
Input lines	3	...
Video outputs	...	1 pcs HDMI 4K 1 pcs VGA
Output lines	3	...
Audio support	...	8 Channels - Audio from cameras
Communication	<ul style="list-style-type: none"> • RS-485 • RACS (Roger) 	...
Audio inputs	...	—
Audio outputs	...	1 pcs CINCH
Image compression method	...	H.265+ / H.265 / H.264+ / H.264
Bitrate	...	max. 50 Mbps
Supported hard drives	...	1 x 6 TB SATA
Recording modes	...	Manual, Motion Detection, Schedule
Main features	<ul style="list-style-type: none"> • Unique EM 125kHz proximity reader built-in • PRT series readers support • 1000 indexed users • History of 250 000 events • 99 General Purpose Schedules • 250 access groups • Tamper detection - removing from mounting surface • Function to prevent of multiple use of the same code/card to gain access (anti-passback) 	...
External storage devices backup	...	Backup to USB drive (pendrive, external drive)
Environment class	IV	...
Operation temp	-25 °C ... 60 °C	...

Searching and playback the records	...	Records searching: by time and events type. Records playback: forward, backward, fast, slow Advanced searching (to the one second accuracy) 1/4/9 channel synchronous playback
Permissible relative humidity	10 ... 95 % (non-condensing)	...
Network interface	...	1 x RJ-45 10/100/1000 Base-TX
Network functions	...	Full support via network, Remote records copying, Web-Server built-in max. 128 on-line users
Network protocols	...	P2P, UPnP, DHCP
ONVIF	...	✓
Default admin user / password	...	admin / 123456
Default IP address	...	DHCP or 192.168.1.30
Web browser access ports	...	80, 554
PC client access ports	...	Port no.: 80 or access by a cloud (P2P)
Mobile client access ports	...	80
Mobile phones support	...	Port no.: 80 or access by a cloud (P2P) • Android: Free application BCS Manager • iOS (iPhone): Free application BCS Manager
RTSP URL	...	rtsp://192.168.1.30:554/unicast/c1/s0/live - Main stream rtsp://192.168.1.30:554/unicast/c1/s1/live - Sub stream
Alarm inputs / outputs	...	—
PTZ control	...	IP Speed Dome Cameras
Motion Detection	...	✓
USB	...	2 x USB 2.0
Mouse support	...	✓
IR remote controller in the set	...	—
Switch PoE	...	8-port PoE Switch built-in, 30 W / Channel, PoE (802.3af/at)
Maximum total switch load	...	75 W
Power supply	10 ... 15 V DC	52 V DC / 1.8 A (power adapter included)
Power consumption	...	max. 9 W (without HDD)
Weight	0.15 kg	0.97 kg
Dimensions	85 x 85 x 27 mm	260 x 243 x 46 mm

Supported languages	...	Polish, English, Czech, French, Spanish, Dutch, German, Portuguese, Slovak, Italian
Manufacturer / Brand	ROGER	BCS BASIC
Guarantee	3 years	3 years