

Code: AI-133

ANTENNA AMPLIFIER AI-133 ALCAD

Net: 19.35 EUR Gross: 19.35 EUR

The AI-133 amplifier is used as subscriber amplifier to distribute the signal of CATV or MATV systems for multiple receivers.

Due to the lack of gaps in the operating band, amplifier can be used in every CATV network. It can be also used to distribute the signals of MATV systems. Amplification adjustment is related to the cable loss characteristics correction.

Amplifier is equipped with passive return channel KZ 0 - 65 MHz, what allows to connecting the cable modem to it. It is possible to use it in installations with wired remote controller extensions e.g. Power Link.



SPECIFICATION

Frequency range:	86 MHz ... 862 MHz 5 MHz ... 65 MHz Return channel
Number of inputs/outputs:	1 / 1 + 1 (1 x test: -15dB)
Input/output impedance:	75 Ω
Connectors type:	"F"
Gain :	24 dB $\pm$ 1 dB , -2.5 dB $\pm$ 0.5 dB Return channel
Gain adjustment:	18 / 13 dB
S/N ratio:	6 dB $\pm$ 1 dB
IMA3 60dB:	110 dB μ V
Return loss:	> 10 dB
Power supply:	230 V AC
Power consumption:	5.5 VA
Manufacturer / Brand:	ALCAD
Guarantee:	2 years

PRESENTATION

View after open the front cover:



Top view:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------