

Code: MC16-PAC-3-KIT

ACCESS CONTROLLER **MC16-PAC-3-KIT** ROGER

The MC16-PAC-3-KIT controller is intended to use in access control systems based on electrical control of door opening.



| | |
|-------------------------------|---|
| Number of served transitions: | 3 |
| Number of supported readers: | 12 pcs |
| Battery backup support: | max. 17 Ah |
| Input lines: | 12 pcs (8 pcs on the mainboard) |
| Output lines: | 8 pcs |
| Communication: | <ul style="list-style-type: none"> • RS-485, • RACS (Roger), • Wiegand |
| Power supply: | 230 V AC |
| Main features: | <ul style="list-style-type: none"> • Two way door control • Power output : 4 x 0.2 A, 4 x 1.0 A • Power adapter : 13.8 V DC / 5.0 A • Battery charging current : 0.3 A / 0.6 A / 0.9 A • Protection against deep discharge of the battery • Tamper detection - opening the enclosure • Place for battery - 12 V / 17 Ah • Metal housing |
| Operation temp: | 5 °C ... 40 °C |



DATA SHEET

| | |
|--------------------------------|--------------------------------|
| Permissible relative humidity: | 10 % ... 95 % (non-condensing) |
| Weight: | 3.2 kg |
| Dimensions: | 305 x 325 x 100 mm |
| Manufacturer / Brand: | ROGER |
| Guarantee: | 3 years |