

Code: KD-132

INVERTER POWER GENERATOR **KD-132** 800 W Kraft&Dele

The use of technology with the use of an inverter allows to obtain a stable output voltage that allows for safe powering of electronic receivers.

The inverter generator is used for emergency power supply, e.g. computers, server rooms, telephones, central heating furnace controllers, digitally controlled household equipment, heat pumps, electrically opened gates and garage gates, various medical devices and other devices sensitive to voltage fluctuations. It is also a convenient power supply in the field of tourism, e.g. caravans, camper-vans, boats, etc.

The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.



Nominal power:	800 W
Maximum power:	1000 W
Output voltage:	230 V AC
Number of outlets:	1 pcs - single-phase
Built-in voltmeter:	—
Output frequency:	50 Hz
Voltage stabilization:	Inverter (provides full voltage stabilization)
12V DC output:	—
Engine capacity:	43 cm ³
Engine type:	2 stroke - air cooled
Starting the engine:	Manual
Noise level during operation:	≤ 82 dBA - work without load (our tests result) ≤ 92 dBA @ 700 W (our tests result)



DATA SHEET

Average fuel consumption:	≤ 0.75 l/h
Fuel tank capacity:	3.5 l
Fuel gauge:	—
Color:	Green + Black
Weight:	8.8 kg
Dimensions:	310 x 240 x 320 mm
Manufacturer / Brand:	Kraft&Dele
Guarantee:	12 months

