

Code: DIGIVOX-2V2

## INTERFACE FOR DIGITAL BROADCASTING **DIGIVOX-2V2**

The DIGIVOX-2V2 is a passive, no power supply system that interfaces the computer with the radio. The device is designed for digital modes that use the sound card as a modem.

DIGIVOX-2V2 has been tested with the following applications: Winlink Express, FLDIGI, JS8Call, WSJT-X, Ham Radio Deluxe, KG-STV.

The interface is dedicated to radios without derived PTT, e.g. Baofeng, Anytone, Kenwood, Woxun, Quansheng.



Device type:	Passive
Connectors type:	<ul style="list-style-type: none"> <li>• PC AUDIO : 2x Jack 3.5 mm socket,</li> <li>• TO RADIO : 4x detachable cable terminals</li> </ul>
PTT output:	"Open Collector" (OC) type max. 30 V / 300 mA
PTT activation time:	20 ms
PTT off time:	5 ms
Minimum value of the audio signal from the sound card:	250 mV RMS
Galvanic isolation:	600 V
Main features:	<ul style="list-style-type: none"> <li>• It allows you to connect any VHF/UHF or KF radio to a computer</li> <li>• Works very well with handheld radios such as Baofeng</li> <li>• Provides full and complete galvanic isolation between radio and computer (600V)</li> <li>• It does not require an external power supply</li> <li>• No need for a serial, parallel or USB port - the connection to the computer is done only through the audio input/output paths of the sound card</li> <li>• Works with most computer applications intended for digital broadcasting, e.g. Packet, PSK31, RTTY, SSTV, FAX</li> <li>• It works very well with the Winlink Express application (electronic mail using radio waves), which allows you to send messages in the absence of Internet via a gateway (e.g. Poznań SR3WLK) or directly (peer-to-peer)</li> </ul>
Operation temp:	-20 °C ... 55 °C
Weight:	0.94 kg



## DATA SHEET

---

Dimensions:	118 x 30 x 59
Manufacturer / Brand:	DELTA
Guarantee:	2 years