

Code: RUD-1

COMMUNICATION INTERFACE **RUD-1** RS-485

Converter between serial transmission interfaces of standards USB and RS-485. Unit is powered straight from the USB port of the PC - doesn't require any external power source. Unit can be used to bi-directional transmission (half duplex) with 0 ... 115.2 kbit/s rate.



Power supply:	5 V DC from USB port
Current consumption:	30 mA
Application:	<ul style="list-style-type: none"> • Communication with RACS access control system • Configuration and management of PR series access controllers from PR Master software • Configuration and management of PRTxxEM and PRTxxMF series readers from RARC software
Permissible relative humidity:	0 ... 95 % (non-condensing)
Dimensions:	100 x 31 x 21 mm
Weight:	0.03 kg
Manufacturer / Brand:	ROGER
Guarantee:	2 years