

# Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order. If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity; 2. Improper results of operation of the product or products related with it;

3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

#### Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

#### Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.





### User Manual Code: GT-N10-004 NVR GT-N10-004 4 CHANNELS GEMINI TECHNOLOGY

The GT-N10-004 digital recorder is a professional device applicable in surveillance systems. The H.264 video compression standard using to record video data, allows to get the best possible quality of recorded image at minimal network transfer and disk storage capacity. The menu options layout has been designed for all users, even beginners can easy navigate and change parameters in DVR settings without any problem.

Due to its dimensions can be used in vehicles and at small areas, where high resistance to environment conditions is required.

Attention! To ensure right operation of the device, turn on the external drive first, and then the recorder.



Standard:	TCP/IP
Supported resolutions:	4 @ 1920 x 1080 px, 4 @ 1280 x 960 px, 4 @ 1280 x 720 px
Video outputs:	1 pcs HDMI 1 pcs VGA
Audio support:	4 Channels
Audio inputs:	Audio from cameras
Audio outputs:	-
Image compression method:	H.264
Operation modes:	<ul> <li>Firmware V4.0[20151231]:</li> <li>4 x Main stream (1920 x 1080) + 4 x Sub stream (960 x 576) + 1 Channel played simultaneously</li> <li>4 x Main stream (1280 x 960) + 4 x Sub stream (960 x 576) + 4 Channels played simultaneously</li> <li>4 x Main stream (1280 x 720) + 4 x Sub stream (960 x 576) + 4 Channels played simultaneously</li> </ul>
Maximal total frame rate:	100 fps @ 1920 x 1080 px, 100 fps @ 1280 x 960 px, 100 fps @ 1280 x 720 px
Supported hard drives:	$1  \mathrm{x}  4  \mathrm{TB}$ - external E-SATA mobile rack required (not included)
Recording modes:	Manual, Motion Detection, Schedule
Network protocols:	ONVIF, 18, 18H, 19, RTSP
External storage devices backup:	Records backup at .mp4 / .avi format to USB (pendrive)
Default admin user / password:	admin / (null)



DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl POL; 60-713 Poznań; Graniczna 10 e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



## User Manual Code: GT-N10-004 NVR **GT-N10-004** 4 CHANNELS GEMINI TECHNOLOGY

Default IP address:	192.168.1.189	
Web browser access ports:	80, 554 - Internet Explorer 80, 1935 - Chrome, Firefox, Opera	
PC client access ports:	5050, 5051, 5052	
Mobile client access ports:	5800	
RTSP URL:	rtsp://ip_address:554/ch01.264 - Main stream, first channel rtsp://ip_address:554/ch01_sub.264 - Sub stream, first channel	
Searching and playback the records:	Records searching: by time and events type. Records playback: forward, backward, fast, slow	
Bitrate:	40 Mbps	
Network functions:	Live image view, Playback the records, Backup the records	
ONVIF:	*	
Operation temp:	-10 °C 55 °C	
Mobile phones support:	Port no.: 5800 or access by a cloud (P2P) • Android: Free application <u>Fseye</u> • iOS: Free application <u>Fseye</u>	
Alarm inputs / outputs:	-	
PTZ control:	-	
Motion Detection:	22 x 18 motion zones	
Mouse support:	×	
IR remote controller in the set:	-	
Power supply:	5 V DC / 2 A (power adapter included)	
Weight:	0.128 kg	
Dimensions:	91 x 89 x 34 mm	
Supported languages:	English, Polish	
Country of origin:	China	
Manufacturer / Brand:	GEMINI TECHNOLOGY	
Guarantee:	2 years	

Device connectors:



GT-N10-004







The device has very small dimensions:





DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl POL; 60-713 Poznań; Graniczna 10 e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------

