

Code: KONW/UNICABLE-II-INV

TV-SAT LNB **KONW/UNICABLE-II-INV** INVERTO

The KONW/UNICABLE-II-INV LNB has been equipped with one UNICABLE output, which allows to connect up to 32 sat-receivers via one coaxial cable, and split the signal on any satellite splitters.

All sat-receivers work fully independently. The condition is that they have a UNICABLE function. The KONW/UNICABLE-II-INV converter works with the 4K Ultrabox+ receiver, model USW4001NCP.



Type:	UNICABLE
Input frequency:	10.7 GHz ... 12.75 GHz

Output frequency:	UNICABLE output : • 1210 MHz - CH1 • 1420 MHz - CH2 • 1680 MHz - CH3 • 2040 MHz - CH4 • 984 MHz - CH5 • 1020 MHz - CH6 • 1056 MHz - CH7 • 1092 MHz - CH8 • 1128 MHz - CH9 • 1164 MHz - CH10 • 1256 MHz - CH11 • 1292 MHz - CH12 • 1328 MHz - CH13 • 1364 MHz - CH14 • 1458 MHz - CH15 • 1494 MHz - CH16 • 1530 MHz - CH17 • 1566 MHz - CH18 • 1602 MHz - CH19 • 1638 MHz - CH20 • 1716 MHz - CH21 • 1752 MHz - CH22 • 1788 MHz - CH23 • 1824 MHz - CH24 • 1860 MHz - CH25 • 1896 MHz - CH26 • 1932 MHz - CH27 • 1968 MHz - CH28 • 2004 MHz - CH29 • 2076 MHz - CH30 • 2112 MHz - CH31 • 2148 MHz - CH32
Oscillator frequency:	10.4 GHz
Number of outputs:	1 pcs F socket - UNICABLE output
Gain :	min. 55 dB
S/N ratio:	0.1 dB
Output impedance:	75 Ω
LNB switch:	DiSEqC 1.x / 2.x
Neck diameter:	40 mm
Main features:	• Independently operation connected in series sat-receivers due to UNICABLE technology • Modern technology eliminates the need for starry wiring • Very low phase noise (LNB recommended for 8PSK HDTV) • The ideal solution in situations where there is only one cable placed from the antenna installation site to home
Weight:	0.15 kg
Dimensions:	123 x 62 x 50 mm
Manufacturer / Brand:	INVERTO
Guarantee:	2 years