

Code: SPU-41-02

SWITCH **SPU-41-02** DiSEqC 2.0 AXING

Switch allows to receive by satellite receiver the channels from 4 satellite positions.
The switch can be installed indoors and outdoors.
Switch operates with most of currently manufactured digital satellite receivers equipped with DiSEqC generator.



SAT frequency range:	950 MHz ... 2200 MHz
Attenuation:	4 dB
Isolation between inputs:	≥ 30 dB
Passing voltage:	✓
DiSEqC:	2.0
Number of inputs:	4 pcs
Number of outputs:	1 pcs
Connectors type:	F type connectors
Operation temp:	-20 °C ... 50 °C
Weight:	0.15 kg
Dimensions:	118 x 108 x 28 mm
Manufacturer / Brand:	AXING
Guarantee:	2 years