

Code: DHI-NKB5000-F

IP / RS-485 KEYBOARD CONTROLLER **DHI-NKB5000-F** DAHUA

Network keyboard with full possibilities of controlling and programming the PTZ camera heads of the DH-SD series. It is also possible to control many DVRs from one keyboard.



Protocols:	DH-SD, Pelco-P, Pelco-D
Cameras numbers (ID):	1 ... 255
Maximal control distance:	• 1200 m @ RS-485 • 15 m @ RS-232
Users + admins:	20 + 1
Connectors:	• RS-485 - cable terminals • RS-232 - 15 pin • 2 x RJ-45 - Gigabit Ethernet • 2 x USB 2.0 • 2 x USB 3.0 • 4 x HDMI • 2 x Jack 3.5 mm socket - Headphones output, External microphone input • SMA socket
Communication standard:	• Network mode - Gigabit Ethernet, RJ-45 socket • Network mode - Wi-Fi • Direct mode - RS-485, terminals • Direct mode - RS-232, D-sub socket • Bluetooth
Manipulator:	3-axis joystick, Speed proportional to the swing (possibility of zoom control by joystick)
Display:	10.2 " LCD - 1280 x 800 px, capacitive touch screen, with light indication
Video output:	4 x HDMI
PTZ control:	• Dahua or other manufacturers Speed Dome cameras • Recorders DAHUA
Alarm inputs / outputs:	4 / 4
Operation modes:	• Normal mode • Matrix mode

Main features:	• Backup to USB drive (pendrive, external drive) • The wireless keyboard included in the kit • Live image view : 4 x 12 Mpx 4 x 8 Mpx 4K UHD 6 x 5 Mpx 8 x 4 Mpx 10 x 3 Mpx 16 x 2 Mpx • Bi-directional audio streaming support • Keypad backlight buttons • Split screen at view from cameras : 1 / 4 / 8 / 9 / 16 • Graphical menu - touch control and by using the buttons or Mouse support
Power supply:	12 V DC / 4 A (power adapter included)
Power consumption:	≤ 25 W
Operation temp. / Relative humidity:	-10 °C ... 55 °C / max. 90 % non-condensing
Weight:	1.90 kg
Dimensions:	425 x 194 x 128 mm
Supported languages:	English
Manufacturer / Brand:	DAHUA
Guarantee:	3 years