

Code: VERSA-KWRL2

WIRELESS KEYBOARD WITH RFID **VERSA-KWRL2** ABAX/ABAX2 SATEL

The device is designed to work within two-way wireless ABAX/ABAX2 system.

The VERSA-KWRL2 keypad is intended for daily operations and programming the VERSA series alarm control system. With the LCD display showing text messages, even advanced functionalities of the alarm control unit are simple and convenient.

The built-in proximity card reader allows to operate the system without the necessity to remember passwords.

Keypad is powered by battery (included) and communicates with alarm control panel using a special radio transmission protocol (bidirectional communication).



Support:	ABAX/ABAX2
Frequency band:	868 MHz ... 868.6 MHz
Radio communication range (at open area):	<ul style="list-style-type: none"> • ≤ 800 m - ABAX2 @ ACU-220, • ≤ 800 m - ABAX2 @ ACU-280, • ≤ 800 m - ABAX @ ACU-120, • ≤ 400 m - ABAX @ ACU-270
Main features:	<ul style="list-style-type: none"> • proximity reader built-in • Large, easily readable LCD with backlight displaying detailed information on system state • Operation status LED indicator • Alarms: keypad hold-down PANIC, FIRE and AUX • Buzzer for acoustic signaling of some system events • Tamper detection - opening the enclosure, removing from mounting surface
Power supply:	2 x CR123A (included)
Color:	White
Operation temp:	-10 °C ... 55 °C
Weight:	0.25 kg
Dimensions:	139 x 124 x 26 mm
Manufacturer / Brand:	SATEL



DATA SHEET

Guarantee:

2 years