

Code: WS-6934

SATELLITE METER **WS-6934**

The WS-6934 satellite meter allows to quick set the satellite dish signal. The WS-6934 is equipped with readable menu, which helps to operate for each installer. The device has implemented over a dozen satellite positions (satellites + transponders).

The WS-6934 model allows to DVB-S/S2 signals measurement.

Attention! The built-in compass is too inaccurate to correctly determine the direction.



Output and input:	— / F plug
Frequency range:	950 MHz ... 2150 MHz
Signal level:	-65 ... -10 dBm
LNB power supply:	13/18 V, max. 400 mA
Switching between bandwidths:	22 kHz
DiSEqC:	1.0, 1.1, 1.2
Modulation:	QPSK, 8PSK, 16APSK
Symbol rate:	2 ... 45 Msps
SCPC and MCPC support:	✓
Programming and firmware upgrade:	RS232
Battery power supply:	• Li-Ion battery 1800 mAh • Power adapter 12 V / 1.5 A (power adapter included)
Display:	240 x 320 " TFT LCD

Main features:	• Sound signaling • Spectrum measurement mode • Signal level is expressed in dBμV, and quality in % • Constellation diagram • Measurement of C/N, S/N, BER • DiSEqC and 22kHz control support • DVB-S signals measurement / DVB-S2 - SD and HD quality channels • Flashlight built-in • UNICABLE 1.0 / 2.0 technology support • Digiturk MDU technology support
Supported languages:	Polish, English, German
Weight:	0.33 kg
Dimensions:	165 x 85 x 40 mm
Guarantee:	2 years