

Code: WWK-951

## PROGRAMMABLE MULTI-RANGE AMPLIFIER **WWK-951** TELMOR



|                                            |                                                                                       |
|--------------------------------------------|---------------------------------------------------------------------------------------|
| Frequency range:                           | 47 MHz ... 108 MHz - FM ,<br>174 MHz ... 230 MHz - VHF ,<br>470 MHz ... 862 MHz - UHF |
| Gain :                                     | 21 dB $\pm$ 2 dB @ FM<br>35 dB $\pm$ 2 dB @ VHF<br>45 dB $\pm$ 3 dB @ UHF             |
| Number of inputs/outputs:                  | 4 / 1                                                                                 |
| Gain adjustment:                           | 0 dB ... 20 dB                                                                        |
| Maximal output level IMD3=60 dB DIN45004B: | 107 dB $\mu$ V @ FM / VHF ,<br>116 dB $\mu$ V @ UHF                                   |
| S/N ratio:                                 | 6 dB @ FM ,<br>5 dB @ VHF ,<br>8 dB @ UHF                                             |
| Power supply:                              | 230 V AC                                                                              |
| Power consumption:                         | 20 W                                                                                  |
| Operation temp:                            | -5 °C ... 50 °C                                                                       |
| Weight:                                    | 0.7 kg                                                                                |
| Dimensions:                                | 257 x 128 x 51 mm                                                                     |
| Manufacturer / Brand:                      | TELMOR                                                                                |
| Guarantee:                                 | 2 years                                                                               |