

Code: BCS-V-XVR0401-AI

AHD, HD-CVI, HD-TVI, CVBS, TCP/IP DVR **BCS-V-XVR0401-AI** 4 CHANNELS BCS View

The BCS-V-XVR0401-AI digital recorder with AHD (Analog High Definition), HD-CVI (High Definition Composite Video Interface), HD-TVI (High Definition Transport Video Interface), TCP/IP and CVBS interface is a professional device applicable in surveillance systems.

The menu options layout has been designed for all users, even beginners can easy navigate and change parameters in DVR settings without any problem.



Standard:	AHD, HD-CVI, HD-TVI, CVBS, TCP/IP
Video inputs:	4 pcs BNC - AHD / HD-CVI / HD-TVI / CVBS
Video outputs:	1 pcs HDMI 1 pcs VGA 1 pcs CVBS - BNC socket
Audio inputs:	1 pcs CINCH, Coaxial audio - Audio from cameras
Audio outputs:	1 pcs CINCH
Image compression method:	H.265+ / H.265 / H.264 / H.264+
Image records resolutions:	• HD-TVI : 4M-N - 1280 x 1440 , 3 Mpx - 1920 x 1536 1 CH only , 1080p - 1920 x 1080 , 960 x 1080 - 1080N , 720p - 1280 x 720 , • AHD / HD-CVI : 4M-N - 1280 x 1440 , 1080p - 1920 x 1080 , 960 x 1080 - 1080N , 720p - 1280 x 720 , • PAL : 960H - 960 x 576 , • IP : max. 6 Mpx - 3072 x 2048
Recording speed adjustment:	6 Mpx IP @ 1 ... 25 fps 4M-N @ 1 ... 15 fps 3 Mpx @ 1 ... 15 fps 1080p @ 1 ... 15 fps 1080N @ 1 ... 25 720p @ 1 ... 25 fps 960H @ 1 ... 25 fps for each channel



DATA SHEET

Operation modes:	4 x HD-TVI / AHD / HD-CVI / CVBS / IP + 2 x IP
Recording modes:	Manual, Sensor, Motion detection, Schedule
Supported hard drives:	1 x 10 TB SATA
External storage devices backup:	Backup to USB drive (pendrive, external drive)
Searching and playback the records:	Records searching: timeline or file list. Playback: forward, fast, slow. Playback max. 4 cameras in the same time
Network interface:	1 x RJ-45 - 10/100 Base-TX
Bitrate:	32 ... 6144 kbps
Network functions:	Network Client Software and IE browser: live view, playback and backup of the records, partial configuration of the recorder parameters
Network protocols:	TCP/IP, PPPoE, DHCP, DNS, DDNS, NTP, SADP, NFS, iSCSI, UPnP, HTTPS, ONVIF
Mobile phones support:	Port no.: 8000 or access by a cloud (P2P) • Android: Free application BCS View • iOS (iPhone): Free application BCS View
Default IP address:	DHCP or 192.168.1.64
Default admin user / password:	admin / - The administrator password should be set at the first start
Web browser access ports:	80
PC client access ports:	554 RTSP, 8000
Mobile client access ports:	8000
Port ONVIF:	80
RTSP URL:	• rtsp://user:password@192.168.1.64:554/Streaming/Channels/channel_no01/ - Main stream • rtsp://user:password@192.168.1.64:554/Streaming/Channels/channel_no02/ - Sub stream
Alarm inputs / outputs:	—
PTZ control:	• Control compatible with coax HD-TVI • RS-485 - PELCO-D/P
Motion Detection:	Split the screen into zones : 22 x 18 motion zones
USB:	2 x USB 2.0
Main features:	• Intelligent Image Analysis : intrusion, crossing the line (tripwire) • Smart motion detection (with recognizing people and vehicles) • Filtering of false alarms based on the recognition of persons and vehicles
Mouse support:	✓
IR remote controller in the set:	—
Power supply:	12 V DC / 1.5 A (power adapter included)
Color:	Black
Weight:	1.15 kg
Dimensions:	315 x 250 x 45 mm



DATA SHEET

Supported languages:	Polish, English, Bulgarian, Croatian, Czech, Danish, Estonian, Greek, Spanish, Dutch, German, Norwegian, Portuguese, Russian, Romanian, Serbian, Slovak, Slovenian, Swedish, Turkish, Hungarian, Italian
Manufacturer / Brand:	BCS View
Guarantee:	3 years