

DATA SHEET

Code: KD-681 INVERTER POWER GENERATOR **KD-681** 3000 W Kraft&Dele



The use of technology with the use of an inverter allows to obtain a stable output voltage that allows for safe powering of electronic receivers.

The inverter generator is used for emergency power supply, e.g. computers, server rooms, telephones, central heating furnace controllers, digitally controlled household equipment, heat pumps, electrically opened gates and garage gates, various medical devices and other devices sensitive to voltage fluctuations. It is also a convenient power supply in the field of tourism, e.g. caravans, camper-vans, boats, etc.

The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.

Nominal power:	3000 W
Maximum power:	3300 W
Output voltage:	230 V AC
Number of outlets:	2 pcs - single-phase
Built-in voltmeter:	-
Output frequency:	50 Hz
Voltage stabilization:	Inverter (provides full voltage stabilization)
12V DC output:	*
Engine capacity:	124.6 cm ³
Engine type:	SY152F-3 1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	\leq 94 dBA



DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl POL; 60-713 Poznań; Graniczna 10 e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



DATA SHEET

Average fuel consumption:	1.1 l/h - 50% load
Fuel tank capacity:	7.51
Fuel gauge:	-
Main features:	 Low oil level indicator light Overload signaling Overload protection Battery charging possible Save fuel by automatically reducing the revs as the load decreases
Color:	Green + Black
Weight:	32.1 kg
Dimensions:	614 x 341 x 506 mm
Manufacturer / Brand:	Kraft&Dele
Guarantee:	12 months

