

Code: FH-8000TR

POWER GENERATOR **FH-8000TR** 3500 W / 7000 VA Honda GX 390 FOGO

Power Generator with manual start used as a power source in the event of power failure in the network or as a substitute power source on a construction site, plot, at home or in a workshop. The Honda engine used in the generator ensures high reliability and high work efficiency.

The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.

The generator is equipped with an Automatic Voltage Regulation system AVR, which allows to eliminate unfavorable voltage fluctuations to a large extent.

The 45-liter fuel tank allows for long periods of uninterrupted operation.



Nominal power:	3500 W - Single-phase installation / 7000 VA @ 0.8 (cosφ) - Three-phase installation
Output voltage:	• 230 V AC, • 400 V AC
Number of outlets:	• 1 pcs - single-phase 16 A (max), • 1 pcs - three-phase 16 A (max)
Built-in voltmeter:	—
Output frequency:	50 Hz
Voltage stabilization:	AVR
12V DC output:	—
Engine capacity:	389 cm ³
Engine type:	Honda GX 390 1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	96 dB
Average fuel consumption:	2.7 l/h - 75 % power



DATA SHEET

Fuel tank capacity:	45 l
Fuel gauge:	✓
Main features:	• Working time with a full fuel tank : 16.7 h - 75 % power, • Low oil level indicator light, • Overload protection, • Silencer with exhaust gas hose connection
Color:	White + Black
Weight:	86.1 kg
Dimensions:	790 x 580 x 650 mm
Manufacturer / Brand:	FOGO
Guarantee:	3 years - The condition is to conduct paid service every year - a warranty inspection at authorized Honda or FOGO service stations, otherwise 12 months