

DATA SHEET

Code: ATLO-SW1-TUYA

SMART LED LIGHTING CONTROLLER ATLO-SW1-TUYA Wi-Fi, Tuya Smart

The ATLO-SW1-TUYA controller allows you to control LED lighting wirelessly via the application or via a connected button. For proper functioning of the device, it is necessary to connect it to the Wi-Fi network with Internet access. In the absence of Wi-Fi, the device can be controlled locally via Bluetooth (previously it must be added to the Tuya platform using Wi-Fi with Internet access).

Beyond direct control, the device has the ability to program the on and off schedule and linking to different system events. It is possible to create action scenarios with other devices. Voice control allows you to control the device via voice commands from Amazon Alexa or the Google Assistant (Internet access required).

Tuya is an international home automation platform that connects thousands of products made by different manufacturers. The system can support all the most popular communication protocols such as Wi-Fi, Zigbee, Bluetooth.

Attention! Controlling the device and schedule settings is possible if the device has access to the Internet.



Application:	switching devices on/off
Number of channels:	1
Power supply:	100 240 V AC, 50 / 60 Hz
Maximal total load:	250 W
Total maximal current:	10 A
Number of inputs:	1
Number of outputs:	1
Connector type:	screw terminals
Wireless:	• Wi-Fi, 2.4 GHz - IEEE 802.11 b/g/n • Bluetooth
Radio communication range:	< 100 m (open area)
Mobile phones support:	The <u>Tuya Smart</u> free application on Android The <u>Tuya Smart</u> free application on iOS



DATA SHEET

Main features:	Local control by physical button , Tuya Smart : schedule, timer, Setting scenarios by different events, remote access, voice control ,
Housing:	Plastic
"Index of Protection":	IP20
Color:	White
Operation temp:	-10 °C 40 °C
Weight:	0.03 kg
Dimensions:	43 x 39 x 22 mm
Guarantee:	2 years