

Code: SP-IR02

## WIRE REMOTE CONTROL REPEATER **SP-IR02** Spacetronek

Wire repeater of the remote controllers for audio-video components allows to control the device, which is located behind closed doors or hidden, for example inside equipment closet.

The IR signal receiver must be fixed in the designated place. IR signal transmitter should be glued in such a way that it covers the "window" for receiving the signal from the remote control on the device.



Number of signal receivers from remote controllers:	1 pcs
Number of emitters:	1 pcs
Length of the cable:	<ul style="list-style-type: none"> <li>• 1.4 m - IR receiver / USB</li> <li>• 2 m - IR receiver / IR transmitter</li> </ul>
IR receiver operation frequency range:	20 ... 60 kHz
Main features:	<ul style="list-style-type: none"> <li>• Single device support</li> <li>• LED indication - IR receiver</li> <li>• Plug &amp; Play</li> <li>• Can be mounted on any flat surface with double-sided adhesive tape attached at the back</li> </ul>
Power supply:	5 V DC - from USB port
Weight:	0.038 kg (total)
Dimensions:	<ul style="list-style-type: none"> <li>• 30 x 17 x 13 mm - Receiver</li> <li>• 13 x 8 x 5 mm - Transmitter</li> </ul>
Manufacturer / Brand:	Spacetronek
Guarantee:	2 years