

Code: BCS-L-NVR0802-A-4KE-8P(2)

NVR **BCS-L-NVR0802-A-4KE-8P(2)** 8 CHANNELS, 8 PoE BCS Line



Standard:	TCP/IP
Supported resolutions:	max. 16 Mpx - 4592 x 3056 px
Video outputs:	1 pcs HDMI 4K 1 pcs VGA
Audio support:	8 Channels - Audio from cameras
Audio inputs:	1 pcs CINCH
Audio outputs:	1 pcs CINCH
Image compression method:	H.265 / H.265+ / H.264 / H.264+ / MJPEG
Supported hard drives:	2 x 16 TB SATA III
Recording modes:	Manual, Sensor, Motion detection, Schedule
Network protocols:	HTTP, HTTPS, TCP/IP, IPv4/IPv6, UPnP, SNMP, UDP, SMTP, NTP, DHCP, DNS, IP Filter, PPPoE, DDNS, FTP, Alarm Server, IP Search, P2P, Auto Register
External storage devices backup:	Backup to USB drive (pendrive, external drive)
Searching and playback the records:	Records searching: by time and events type. Records playback: forward, backward, fast, slow Advanced searching (to the one second accuracy) All channels synchronous playback, Smart Search function
Bitrate:	max. 256 Mbps
Network functions:	• Full support via network • Remote records copying • Web Server built-in max. 128 on-line users
ONVIF:	✓
Mobile phones support:	Port no.: 37777 or access by a cloud (P2P) • Android: Free application BCS Manager • iOS (iPhone): Free application BCS Manager
Default IP address:	192.168.1.108



DATA SHEET

Default admin user / password:	admin / - The administrator password should be set at the first start
Web browser access ports:	80, 37777
PC client access ports:	37777
Mobile client access ports:	37777
RTSP URL:	rtsp://admin:haslo@192.168.1.108:554/cam/realmonitor?channel=1&subtype=0 - Main stream rtsp://admin:haslo@192.168.1.108:554/cam/realmonitor?channel=1&subtype=1 - Sub stream
Alarm inputs / outputs:	4 pcs / 2 pcs - Relay output
PTZ control:	Speed Dome cameras, motor units, Motozoom cameras/lenses support
Intelligent Image Analysis:	✓
Motion Detection:	✓
USB:	1 pcs USB 2.0 1 pcs USB 3.0
Main features:	Functions implemented in cooperation between the recorder and cameras that support these functions • Fisheye-Dewarping - correction of the "fish eye" view to the perspective view • ANR - Automatic Network Replenishment allows to save image to the card when the network connection with DVR is break (network failure) and next synchronize its Cooperation with POS (Point of Sale) terminals
Mouse support:	✓
IR remote controller in the set:	✓
Switch PoE:	8-port PoE Switch built-in, 25.5 W / Channel, PoE (802.3af/at)
Maximum total switch load:	130 W
Power supply:	100 ... 240 V AC @ 50 / 60 Hz
Operation temp:	-10 °C ... 55 °C
Weight:	2.58 kg
Dimensions:	374 x 320 x 53 mm
Supported languages:	Polish, English
Manufacturer / Brand:	BCS Line
Guarantee:	3 years