

Code: RV-4/8PR

## VIDEO SPLITTER **RV-4/8PR**

The RV-4/8PR video splitter allows to split video signals. The device is designed to continuous work in closed spaces. The device works with color and b/w cameras at all TV standards PAL. The proper distances among sockets allow to easy BNC connectors mounting.

The RV-4/8PR video splitter default configuration is 4 independent video splitters 1/2. The device can be easily programmable by jumpers, which you can see after remove the cover. There are 5 configurations available, which are presented below. Vertical jumpers activate inputs, horizontal jumpers connect outputs. It is easy to re-program the array using jumpers located on the front panel. There are 5 combinations available. The example four ones are given in the figures. When programming, the table of possible combinations should be employed. The vertical jumpers activate respective inputs and the horizontal ones - connect respective outputs.



Standard:	CVBS - PAL, NTSC
Number of inputs:	4 pcs BNC
Number of outputs:	8 pcs BNC
Bandwidth:	0 ... 40 MHz (-3dB)
Inputs impedance:	75 $\Omega$
Outputs impedance:	75 $\Omega$
Outputs configuration:	✓
Power supply:	12 V DC (power adapter not included)
Current consumption:	80 mA
Gain :	0 dB
Weight:	0.220 kg
Dimensions:	213 x 36 x 93 mm
Manufacturer / Brand:	DELTA
Guarantee:	<b>3 years</b>