



User Manual

Code: APTI-KIT-WIFI-S-20C2
SURVEILLANCE KIT **APTI-KIT-WIFI-S-20C2** Wi-Fi, 4 CHANNELS - 1080p

Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order.

If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity;
2. Improper results of operation of the product or products related with it;
3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

The surveillance kit includes 4 cameras, Wi-Fi DVR with Seagate 1TB hard disk, and 4 power adapters DC 12V/500mA for independent camera power supply. The kit has been pre-configured in a way that allows to start working immediately after removing from the box and connecting the power supply. The H.265 / H.264 video compression standard using to record video data, allows to get the best possible quality of recorded image at minimal network transfer and disk storage capacity.

Cameras included in the kit are equipped with additional functions: 2 with built-in PIR detectors, 1 with gas and carbon monoxide detector and 1 with sound alarm signalling device. Additional camera functions are fully supported and managed by the recorder. The recorder allows to perform several different actions after the alarm is triggered by the detector located in the camera: start recording the image from the camera that triggered the alarm; sound alarm from a camera equipped with a loudspeaker; sound alarm from the loudspeaker built into the recorder; sending an e-mail.

Network Video Recorder allowing to operate with Wi-Fi Apti cameras supported 802.11 b/g/n standards. The menu options layout has been designed for all users, even beginners can easy navigate and change parameters in DVR settings without any problem.

IP camera with efficient H.264 / H.265 image compression algorithm for clear and smooth video streaming at maximal resolution of 1920 x 1080 (1080p). The used Wi-Fi module allows to remote communication with camera for max. distance up to 300 m. In fact, it is a range of several dozen meters and depends on obstacles between the antennas.

Attention! The DVR has installed the Seagate 1TB ST1000VX005 hard disk.



Standard:	TCP/IP
Supported resolutions:	max. 5 Mpx - 2592 x 1944 px
Audio support:	4 Channels - Audio from cameras
Video outputs:	1 pcs HDMI 1 pcs VGA
Audio inputs:	—
Audio outputs:	1 pcs Jack 3.5 mm socket
Image compression method:	H.265 / H.265+ / H.264 / H.264+
Supported hard drives:	1 x 8 TB SATA, included 1 TB Seagate
Recording modes:	Manual, Sensor, Motion detection, Schedule
Network protocols:	ONVIF, Private
External storage devices backup:	Records backup at (.avi) format to USB (pendrive)
Searching and playback the records:	Records searching: timeline or file list. Playback: forward, fast Channels played simultaneously : 1 @ 5 Mpx / 2 @ 3 Mpx / 4 @ 1080p
Network functions:	Network Client Software and IE browser: live view, playback and backup of the records, configuration of the recorder parameters Full support via network, Remote records copying, Web Server built-in Wi-Fi : 2.4 GHz - Apti cameras support, Range : 300 m (open area)
Bitrate:	28 Mbps



User Manual

Code: APTI-KIT-WIFI-S-20C2
SURVEILLANCE KIT **APTI-KIT-WIFI-S-20C2** Wi-Fi, 4 CHANNELS - 1080p

ONVIF:	2.4
Mobile phones support:	Access by a cloud (P2P) <ul style="list-style-type: none">• Android: Free application BitVision, Android: Free application iVMS320• iOS (iPhone): Free application BitVision, iOS: Free application iVMS320
Default IP address:	172.136.123.88
Default admin user / password:	admin / 12345
Web browser access ports:	80, 443, 554
PC client access ports:	80, 443, 554
Port ONVIF:	80
Alarm inputs / outputs:	—
PTZ control:	—
Motion Detection:	Split the screen into zones : 24 x 18 motion zones
Mouse support:	✓
IR remote controller in the set:	—
Power supply:	12 V DC / 2 A (power adapter included)
Weight:	1.09 kg
Dimensions:	260 x 220 x 45 mm
Supported languages:	Polish, English, Bulgarian, Czech, French, Spanish, German, Portuguese, Russian, Turkish, Hungarian, Italian

Camera:

Standard:	TCP/IP
Sensor:	1/3 " Sony CMOS IMX323
Matrix size:	2.1 Mpx
Scanning system:	Progressive
Resolution:	1920 x 1080 - 1080p
Operation modes:	Main and sub streams may be in any configuration Firmware 3516EV100_F23_W30T0A0M4C0_W_8.1.29.2 <ul style="list-style-type: none">• Main stream : 1920 x 1080• Sub stream : 720 x 480, 640 x 480• Sub stream 2 : 352 x 288
Lens:	3.6 mm
View angle:	<ul style="list-style-type: none">• 67 ° (manufacturer data)• 78 ° (our tests result)
Range of IR illumination:	25 m
S/N ratio:	≥ 52 dB
RS-485 interface:	—
Memory card slot:	—
Image compression method:	H.265 / H.265+ / H.264 / H.264+ / MJPEG



User Manual

Code: APTI-KIT-WIFI-S-20C2
SURVEILLANCE KIT **APTI-KIT-WIFI-S-20C2** Wi-Fi, 4 CHANNELS - 1080p

Alarm inputs / outputs:	—
Audio:	—
Main stream frame rate:	20 fps @ 1080p
Network interface:	10/100 Base-T (RJ-45) Wi-Fi - 2.4 GHz, IEEE 802.11 b/g/n
Network protocols:	TCP/IP, ICMP, HTTP, HTTPS, FTP, DHCP, DNS, DDNS, RTP, RTSP, RTCP NTP SMTP
ONVIF:	2.4
Mobile phones support:	Access by a cloud (P2P) • Android: Free application iVMS320 , Android: Free application BitVision • iOS: Free application iVMS320
Default IP address:	192.168.1.168
Default admin user / password:	admin / admin
Web browser access ports:	80, 443, 554
PC client access ports:	80, 443, 554
Port ONVIF:	8999
WEB Server:	Built-in
Max. number of on-line users:	10
RTSP URL:	rtsp://user:password@ip_address:554/0 - Main stream rtsp://user:password@ip_address:554/1 - Sub stream
Main features:	<ul style="list-style-type: none">• Wi-Fi module - IEEE 802.11 b/g/n, Range : 300 m (open area) ; Antenna - SMA socket• WDR - Wide Dynamic Range• DNR - Digital Noise Reduction• F-DNR (Defog) - Reduction of image noise caused by precipitation• BLC/HLC - Back Light / High Light Compensation• Possibility to change the resolution, quality and bit rate• Motion Detection• Configurable Privacy Zones• Mirror - Mirror image• Sharpness - sharper image outlines• Each of the cameras is equipped with an additional function : 2 pcs PIR detector 1 pcs Gas and carbon monoxide detector 1 pcs Alarm siren
Power supply:	12 V DC / 500 mA
Power consumption:	≤ 6 W
Housing:	Compact - Plastic
Color:	White
Vandal-proof:	—
"Index of Protection":	—
Operation temp:	-10 °C ... 50 °C
Weight:	0.19 kg

Dimensions:	68 x 88 x 157 mm
Supported languages:	English, Bulgarian, Czech, French, Spanish, German, Polish, Portuguese, Russian, Turkish, Hungarian, Italian
General information:	
Connecting cable:	—
Power adapter:	4 pcs : 12 V / 500 mA , 1 pcs : 12 V / 2 A
Country of origin:	China
Manufacturer / Brand:	APTI
Guarantee:	2 years

DVR:



Rear view:



Internal view:



Cameras:
with PIR detector:



with sound signalling:



with gas detector:



Front view:



Side view:



Camera mounting side view:



In the kit:



Package:



User Manual

Code: APTI-KIT-WIFI-S-20C2

SURVEILLANCE KIT **APTI-KIT-WIFI-S-20C2** Wi-Fi, 4 CHANNELS - 1080p



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------