

Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order. If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity; 2. Improper results of operation of the product or products related with it;

3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

IP camera with efficient H.264 / H.265 image compression algorithm for clear and smooth video streaming at maximal resolution of 2688 x 1520 (4.0 MPx).

PoE powering possibility, compatible with the 802.3af standard makes the device more universal and easier to install. Camera is according to IP66 Index of Protection norm.





DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl POL; 60-713 Poznań; Graniczna 10 e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

IPC-HDB4431C-AS-0280B



Standard:	TCP/IP	
Sensor:	1/3 " Progressive Scan CMOS	
Matrix size:	4.0 Mpx	
Scanning system:	Progressive	
Resolution:	2688 x 1520 - 4.0 Mpx 2560 x 1440 - 3.6 Mpx 2304 x 1296 - 3.0 Mpx 1920 x 1080 - 1080p 1280 x 1024 - 1.4 Mpx 1280 x 960 - 1.3 Mpx 1280 x 720 - 720p	
Lens:	2.8 mm	
View angle:	104 °	
S/N ratio:	> 50 dB	
RS-485 interface:	-	
Image compression method:	H.265 / H.264 / MJPEG	
Alarm inputs / outputs:	-	
Audio:	Microphone built-in	
Bitrate:	24 9472 kbps - H.264 14 9984 kbps - H.265	
Main stream frame rate:	25 fps @ 4.0 Mpx	
Network interface:	100/1000 Base-T (RJ-45)	
Network protocols:	HTTP, HTTPS, TCP/IP, IPv4, UDP, SMTP, FTP, DHCP, DDNS, NTP, DNS, ARP, RTSP, RTP, UPnP	
Memory card slot:	Micro SD memory cards up to 128GB support (possible local recording)	
Mobile phones support:	Port no.: 37777 or access by a cloud (P2P) • Android: Free application <u>DMSS</u> • iOS (iPhone): Free application <u>DMSS</u>	
Default admin user / password:	admin / admin	
Default IP address:	192.168.1.108	
Web browser access ports:	80, 37777	
PC client access ports:	37777	
Mobile client access ports:	37777	
Port ONVIF:	80	
RTSP URL:	rtsp://admin:hasło@192.168.1.108:554/cam/realmonitor?channel=1&subtype=0 - Main stream rtsp://admin:hasło@192.168.1.108:554/cam/realmonitor?channel=1&subtype=1 - Sub stream	
WEB Server:	Built-in	
Max. number of on-line users:	20	





ONVIF:	2.42	
Main features:	 3D-DNR - Digital Noise Reduction WDR - 120 dB - Wide Dynamic Range Possibility to change the resolution, quality and bit rate Time mark and image description Image rotation and mirror Configurable: brightness, contrast, saturation Privacy zones Motion Detection Audio detection IVS analysis : crossing the line (tripwire), intrusion, scene changing, abandoned/missing object, face detection 	
Power supply:	• PoE (802.3af), • 12 V DC / 250 mA	
Power consumption:	≤ 3 W	
Housing:	Dome - Metal	
Vandal-proof:	×	
Color:	White	
Operation temp:	-30 °C 60 °C	
"Index of Protection":	IP66	
Weight:	0.27 kg	
Dimensions:	Ø 110 x 56 mm	
Supported languages:	Polish, English	
Manufacturer / Brand:	DAHUA	
Guarantee:	3 years	

Camera view after remove the Dome cover:









Mounting dimensions:



See how to initialize DAHUA cameras:

In the kit:

:



DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl POL; 60-713 Poznań; Graniczna 10 e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



(a)hua	
Dahua HD Mini Network Dome Camera Ouick Start Guide Version 1.00	
Dahua Technology CO., LTD	0

PACKAGE

Dimensions (L x W x H): 0x0x0 mm Gross Weight: 0 kg

