

## Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order.

If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity;
2. Improper results of operation of the product or products related with it;
3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

### Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

**Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.**

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

### Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

The ETIGER-S3B-S alarm set is an ideal solution for people looking for a simple and reliable alarm system for home applications. Thanks to wireless communication between the system components and its simple and intuitive configuration by phone, SMS or via a mobile application, there is no need to call the installer to install the devices.

The set includes: eTiger-S3b Sim Secual wireless alarm control panel, two ES-D1A wireless motion detectors, two ES-D3C wireless reed switches, two ES-RC1N wireless keyfobs and two ES-T1A RFID keyfobs.



Number of supported wireless devices:	max. 60 pcs
Number of supported remote control keyfobs:	max. 10 pcs, In the kit : 2 pcs
The RFID cards/keyfobs support:	max. 50 pcs, In the kit : 2 pcs
Number of supported wireless sirens:	max. 50 pcs (not included)
PIR detectors included:	2 pcs, Wireless
Magnetic contact included:	2 pcs, Wireless
Enclosure included:	✓
Keyboard included:	✓
Expander included :	—
Wireless:	433 MHz
Operating range in open area:	max. 80 m
Zones:	50
Built-in modules:	GSM
Access from PC:	—
Mobile phones support:	<ul style="list-style-type: none"> <li>• Operation via telephone call using tone dialing,</li> <li>• Remote control of the control panel via SMS,</li> <li>• Android: Free application <a href="#">eTIGER Home</a>,</li> <li>• iOS (iPhone): Free application <a href="#">eTIGER Home</a></li> </ul>
Main features:	<ul style="list-style-type: none"> <li>• Bidirectional communication,</li> <li>• Configuration and full control over the system by phone (call, SMS or application),</li> <li>• LED indication,</li> <li>• Built-in alarm siren - 100 dB,</li> <li>• Alarm mute function</li> </ul>



# User Manual

Code: ETIGER-S3B-S  
ALARM KIT **ETIGER-S3B-S**

Power supply:	<ul style="list-style-type: none"><li>• 12 V DC / 1 A (power adapter included)</li><li>• Built-in battery that maintains the control panel operation during a power failure : 2 x 3.7 V / 800 mAh</li></ul>
Housing:	Plastic
Color:	White
Operation temp:	-10 °C ... 55 °C
Weight:	0.32 kg
Dimensions:	187 x 130 x 26 mm

## MAGNETIC CONTACT:

Detection:	Opening the door or window
Alarm signaling:	Signal to control panel
Frequency range:	433 MHz
Radio communication range (at open area):	max. 80 m
Alarm inputs:	—
Main features:	<ul style="list-style-type: none"><li>• Tamper protections</li><li>• Low battery level alarm</li></ul>
Battery:	1 x LR3 (AAA) 1.5 V (included)
Operation temp:	-10 °C ... 55 °C
Weight:	<ul style="list-style-type: none"><li>• 0.034 kg - Transmitter</li><li>• 0.012 kg - Magnet</li></ul>
Dimensions:	<ul style="list-style-type: none"><li>• 60 x 45 x 18 mm - Transmitter</li><li>• 45 x 19 x 18 mm - Magnet</li></ul>

## PIR DETECTOR:

Application:	Indoor
Sensor type:	Passive Infra Red (PIR)
Frequency range:	433 MHz
Radio communication range (at open area):	max. 80 m
Detection range / Detection angle:	8 m / 110 °
Sensitivity adjustment:	—
Pet immunity:	—
Digital temperature compensation:	—
Alarm output:	Wireless
Main features:	<ul style="list-style-type: none"><li>• Tamper protections - opening the cover</li><li>• Low battery level alarm</li><li>• LED indicator</li></ul>
Housing:	Plastic
Color:	White
Battery:	2 x LR6 (AA) 1.5 V (included)

Operation temp:	-10 °C ... 55 °C
Weight:	0.094 kg
Dimensions:	107 x 53 x 33 mm

#### REMOTE CONTROL:

Frequency band:	433 MHz
Radio communication range (at open area):	max. 80 m
Main features:	<ul style="list-style-type: none"> <li>• LED indication</li> <li>• Large, readable buttons : arm, disarm, arming only perimeter protection zones, SOS</li> <li>• Configuration is done using the mobile application</li> <li>• Alarm mute function</li> </ul>
Battery:	CR2025 3 V (included)
Operation temp:	-10 °C ... 55 °C
Weight:	0.02 kg
Dimensions:	55 x 32 x 11 mm

#### General information:

Manufacturer / Brand:	eTIGER
Guarantee:	2 years

#### Alarm control panel:



#### Front panel:



Rear view:





Connectors:



Motion detector:



Front panel:



Rear view:





Place for batteries 2 x 1.5V AA:



Reed switch:



Rear view:



Place for batteries 1 x 1.5V AAA:



In the kit:



## PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------