



User Manual

Code: CS-H9-70HG
MULTI-FUNCTIONAL CCTV TESTER **CS-H9-70HG**

Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order.

If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity;
2. Improper results of operation of the product or products related with it;
3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

Multi-functional tester of AHD, HD-CVI, HD-TVI, IP cameras, analog cameras, Speed Dome (PTZ) cameras has implemented many additional functions, necessary during initialization of the CCTV installation system.



Video standard:	• AHD - 8 Mpx, • HD-CVI - 8 Mpx, • HD-TVI - 8 Mpx, • HD-SDI - 8 Mpx, • TCP/IP - 8K @ H.265 / 4K @ H.264, • CVBS - PAL / NTSC
Display:	7 " Retina - capacitive touch screen, 1280 x 800 px
Video input:	• 1 pcs AHD / HD-CVI / HD-TVI / CVBS - BNC socket • 1 pcs HD-SDI - BNC socket • 1 pcs VGA • 1 pcs HDMI
Video output:	• 1 pcs CVBS - BNC socket • 1 pcs VGA • 1 pcs HDMI
Port LAN:	2 pcs - PoE cameras and switches support
Audio input:	1 pcs Mini Jack
Audio output:	1 pcs Mini Jack
Video signal level meter:	AHD, HD-CVI, HD-TVI, CVBS : Peak level, Sync level, Burst
Video signal generator:	—
Serial ports:	RS-485



User Manual

Code: CS-H9-70HG
MULTI-FUNCTIONAL CCTV TESTER **CS-H9-70HG**

Protocols:	Support for over 30 RS485 protocols : Pelco-D, Pelco-P, YAAN, YAAN-O, YAAN-1, SAMSUNG, PANASONIC, Lilin-FAST, Lilin-MLP2, MOLYNX, MINKING A01, Fastrax, CBC, LC-NEW, WV-CS850, SONY-EVI, LG-MULTIX, DAT-SD, VICON, Vcltp, DH-YTC 06, Santachi, Bosch OSRD, TeleEye DM2, HD 600, Hikvision, KALATEL ASC, AD 168(M-B), SAMSUNG SPD, Siemens, Cohu, MINKING B01, ALEC
Baud rates:	150, 300, 600, 1200, 2400, 4800, 9600, 19200, 38400, 115200 b/s
LAN (twisted-pair) or telephone cables testing:	UTP cables or phone lines connecting test with RJ-45 connectors
RS-485, RS-232 lines test:	Data analysis from control device (the commands are displayed in hexadecimal)
Wi-Fi module:	✓
Identification the wire in the group of wires:	✓
Audio test:	✓
Digital multimeter:	Measurement : voltage, current, resistance, continuity test, diode test, electrical capacity
Optical power measurement:	Optical power measurement in fiber optic networks (ST and SC adapters) Optical wavelength : 850, 1300, 1310, 1490, 1550, 1625 nm Range : -70 ... +10 dBm
VLS (VFL) - Visual Fault Locator of fiber cable:	Laser LD, 650 nm, 10 mW
TDR reflectometer:	Detecting and locating a cable break (UTP only)
Operation as power source:	• 5 V DC / 2 A from USB port • 12 V DC / 3 A • 24 V DC / 2 A • 48 V (PoE, LAN), 30 W
Battery power supply:	• Li-Ion battery : 7.6 V / 7800 mAh • 12 V DC / 2 A (power adapter included)
Estimated battery operation time:	max. 16 hours
Operation:	Graphical menu - touch control and by using the buttons



User Manual

Code: CS-H9-70HG
MULTI-FUNCTIONAL CCTV TESTER **CS-H9-70HG**

Main features:	• AHD cameras test • HD-CVI cameras test • HD-TVI cameras test • PAL/NTSC cameras test • HD-SDI cameras test • IP cameras test - Supported image compression methods : H.265, H.264, MJPEG • Searching and view of IP cameras compatible with Onvif • Motor units and PTZ (Speed Dome) cameras control • IP cameras view from embedded applications - Hik test tool, DH test tool, HW tool, UNV test tool, JOVISION tool, TOPSEE tool, JCO test tool, TVT tool, Tiandy tool • Embedded Internet browser - Google Chrome • Test signal generator • LAN connections monitoring • IP addresses scanner • PING - test the link using ICMP packets • Detection of the connected port in switch • LAN (twisted-pair) cables testing • PoE cameras and switches support • PoE power meter • DC 5V / 12V / 48V power source • Identification the wire in the group of wires • TDR reflectometer • Optical power meter • VLS (VFL) - Visual Fault Locator of fiber cable • Digital Multimeter • Data monitor - serial port data analysis RS-485 • The Cable tracer application - easy cable location in a disordered bundle • Audio test • Hotspot - Wi-Fi • Video recording to micro SD card with playback possibility - 8 GB included • Playback the records • VLC Media Player application installed - the ability to play multimedia files in many popular formats (.mp3, .mp4, .avi, .mpeg and others) • Calculator • Quickoffice package installed - creation and reading of .docx text documents, .xlsx spreadsheets and .pptx multimedia presentations • Flashlight built-in • The ability to change the display theme and background • Illuminated buttons • Built-in camera (possibility to take photos and record videos) • Laser Rangefinder : 100 m $\pm$ 3 mm • Lens simulator - an application that allows you to select the appropriate parameters of the camera for mounting in a given place • SFP socket • GPS module
Operation temp:	-10 °C ... 50 °C
Permissible relative humidity:	30 % ... 90 %
Weight:	1.17 kg
Dimensions:	276 x 163 x 44 mm
Supported languages:	Polish, English, Czech, French, Greek, Spanish, German, Portuguese, Russian, Serbian, Turkish, Italian
Guarantee:	2 years

Connectors:



Rear view:



Place for battery:



Wire tracer:





Connectors:





Main menu:





User Manual

Code: CS-H9-70HG
MULTI-FUNCTIONAL CCTV TESTER **CS-H9-70HG**



DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



In the kit:



The tester with accessories housed in a handy bag:



PACKAGE



User Manual

Code: CS-H9-70HG
MULTI-FUNCTIONAL CCTV TESTER **CS-H9-70HG**

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------