



User Manual

Code: WWK-ALPHA+
DIGITAL SELECTIVE AMPLIFIER **WWK-ALPHA+** TELMOR

Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order.

If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity;
2. Improper results of operation of the product or products related with it;
3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

WWK-ALPHA+ is a digital selective amplifier. This device will be the best choice as a first active device in terrestrial television signal distribution network and other signals (e.g. using ports AUX, DAB, FM).

Each DVB-T/T2 signal can be configured separately according to input and desired output frequency as well as output level. Additionally, it is also possible to check the output power level at selected frequencies (dynamic measurement). Installation and parameter adjustment are done by local manipulator and are visible on large display.

The device has a built-in LTE,5G signal filter that eliminates unwanted signals in the 700/800 MHz band intended for the implementation of data transmission services (LTE,5G). Thanks to the possibility of powering the preamplifiers, it is not necessary to use power inserters in the case of using active antennas. (VHF/UHF1-4). Test point with 30dB attenuation will allow you to use it for measurements on simple meters or for connecting the signal to optical distribution systems without additional accessories in the form of attenuators.



Frequency range:	<ul style="list-style-type: none"> • 87.5 MHz ... 108 MHz - FM, • 170 MHz ... 230 MHz - VHF / DAB, • 470 MHz ... 862 MHz - UHF, • 47 MHz ... 862 MHz - AUX
Gain :	<ul style="list-style-type: none"> • 35 / 25 dB @ FM • > 70 dB @ VHF / DAB • > 70 dB @ UHF • 22 / 10 dB @ AUX
Number of inputs/outputs:	6 / 1 + 1 (test, -30dB)
Pre-amplifiers powering:	12 V DC : 50 mA / VHF/UHF 1-4 input
Gain adjustment:	<ul style="list-style-type: none"> • 0 dB ... 20 dB (FM/DAB/VHF/UHF) • 0 dB ... 20 / 10 dB (AUX)
Cable loss correction:	0 dB ... 9 dB (DAB/VHF/UHF)
Maximal output level DIN45004B:	<ul style="list-style-type: none"> • 118 dBμV (FM/DAB/VHF/UHF), • 112 dBμV (AUX)
Return loss:	> 10 dB
S/N ratio:	< 7 dB @ FM



User Manual

Code: WWK-ALPHA+
DIGITAL SELECTIVE AMPLIFIER **WWK-ALPHA+** TELMOR

Main features:	<ul style="list-style-type: none">• DVB-T, DVB-T2, DAB, DAB+ compliance• Digital signal processing• 32 channel filters - selectivity > 35 dB• High isolation between inputs : > 35 dB• Built-in LTE / 5G filter• Automatic and manual preamplifier adjustment• AGC Automatic Gain Control for all channels• Minimum input level : 40 dBμV• Power input signals measurement• Auto output power equalization• Adjustable cable power loss correction• Individual adjustment of output levels• Large, readable LCD display• One-touch action buttons• Built-in European channel plan• Channel scan function• Protections : Overvoltage, Short-circuit• DAB mode (VHF bandwidth) with level adjustment• AUX port for connecting a modulator or a headend• Port USB• Test point -30dB
Power supply:	12 V DC / 2 A (power adapter included)
Power consumption:	20 W (max)
Operation temp:	0 °C ... 50 °C
Weight:	0.68 kg
Dimensions:	200 x 190 x 51 mm
Manufacturer / Brand:	TELMOR
Guarantee:	2 years

Top view:



Connectors:





Power socket:



In the kit:



PACKAGE



User Manual

Code: WWK-ALPHA+
DIGITAL SELECTIVE AMPLIFIER **WWK-ALPHA+** TELMOR

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------