

Code: R19-22U/600

STANDING RACK CABINET R19-22U/600

Net: 2 986.15 NOK Gross: 2 986.15 NOK

More and more home devices to LAN, RTV, CCTV installations are made with a view to the RACK system, so that their installation is aesthetically pleasing, and that devices are protected against accidental mechanical damages.

The R19-22U/600 cabinet is suitable for mounting all sorts of devices in standard 19" rack housings. Ideal solution for installing DVRs, power units, splitters, headends, network devices, etc. Inside the cabinet can be also place the devices that are not in standard RACK-19" housings, for example DVRs, multiswitches, RTV-SAT amplifiers, modulators. For this purpose the user should mount additional shelf/shelves available for RACK cabinet.

The RACK cabinet has many openings ensuring adequate air circulation. Additionally, it is possible to install fans to increase the ventilation.



SPECIFICATION

| | |
|------------------|---|
| Internal width: | 19 " |
| Internal height: | 22 U |
| External width: | 600 mm |
| External height: | 1200 mm |
| External depth: | 600 mm |
| Color: | Black RAL9004 |
| Door: | <ul style="list-style-type: none">• Front: glass• Side: metal, snap-in• Rear: metal, hinges |
| Main features: | <ul style="list-style-type: none">• Holes for cables: in rear panel, on top, in the bottom• Removable side panels• Possibility to mount the door as left or right• 2 keys included, 2 shelves 4-point mounted• Four rack rails for mounting devices (2x front, 2x rear)• Framework with bearing strength of 500 kg is made of high toughness steel |
| Weight: | 55 kg |
| Guarantee: | 2 years |

PRESENTATION

Cabinet without side panels, with opened front door:

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



View of the cabinet lock:



In the kit:



PACKAGE

| | |
|----------------------------------|--------------------|
| Dimensions (L x W x H): 0x0x0 mm | Gross Weight: 0 kg |
|----------------------------------|--------------------|