

	SMART LED LIGHTING CONTROLLER WLIGHTBOX-S-PRO/BLEBOX Wi-Fi, 12 ... 24 V DC	WIRELESS PIR DETECTOR HECKERMANN-MODEL-2
		
	244.33 DKK 244.33 DKK	36.15 DKK 36.15 DKK
Support	...	Heckermann
Battery power supply	...	9 V 6F22 (included)
Application	Works with LED lighting - single-color (MONO) 12-24V LED strips	...
Frequency range	...	433 MHz
Rated voltage	12 ... 24 V DC	...
Radio communication range (at open area)	...	max. 30 m
Maximal total load	120 W	...
Recommended installation height	...	2.2 m
Total maximal current	5 A	...
Number of inputs	1	...
Detection angle / Detection range	...	110 ° / 12 m (basic lens)
Number of outputs	1	...
Pet immunity	...	—
Connector type	screw terminals	...
Wireless	Wi-Fi, 2.4 GHz - IEEE 802.11g	...
Mobile phones support	<ul style="list-style-type: none"> • The wBox free application on Android • The wBox free application on iOS 	...

Main features	<ul style="list-style-type: none"> • Local control by physical button, • schedule, • timer, • remote access, • voice control, • Lighting on/off and brightness control, • Absence mode - enables random turn on and off the lighting simulating the presence of household members, • Omnidirectional antenna • Wi-Fi 5 dB, • SMA-RP socket • μWiFi technology support 	<ul style="list-style-type: none"> • Code 1527 data encryption • Interchangeable Fresnel lenses • Temperature compensation • Tamper detection - opening the enclosure
Housing	<ul style="list-style-type: none"> • Non-halogen plastic, Self-extinguishing • Waterproof, Weatherproof 	...
"Index of Protection"	IP54	...
Color	Black	...
Operation temp	-20 °C ... 50 °C	0 °C ... 50 °C
Weight	0.094 kg	0.11 kg
Dimensions	<ul style="list-style-type: none"> • 92 x 52 x 28 mm - without antenna • 230 x 85 x 28 mm - with antenna, vertical • 197 mm - Antenna 	60 x 110 x 47 mm
Manufacturer / Brand	BleBox	Heckermann
Guarantee	2 years	2 years