




	TIME & ATTENDANCE RECORDER DS-K1A802EF-B Hikvision	MECHANICAL SPLICE FAST-MS1*P5	POWER SUPPLY ADAPTER 12V/1A/5.5-ZOL
			
	189.22 EUR 189.22 EUR	7.80 EUR 7.80 EUR	15.16 EUR 15.16 EUR
Adapter type	Transforming
Identification time	< 1 s
Input voltage	230 V AC
FAR (False Acceptance Rate)	≤ 0.001 %
FRR (False Rejection Rate)	≤ 0.01 %
AC input frequency	47 ... 63 Hz
In package	...	5 pcs The price for package	...
Output voltage	12.0 V DC
Fiber type	...	Multi-mode and single-mode	...
Cards support	Unique EM 125kHz
Output voltage adjustment	—
Fiber diameter	...	125 μm	...
Reading distance of prox-keys	max. 5 cm
Output current	1.0 A
Keyboard built-in	✓
Output power	12.0 W
Cable diameter	...	250 μm / 900 μm	...
Doorbell button	—
Number of outputs	1 pcs
IL	...	0.1 dB/km (for 1310 and 1550 nm)	...
Relay output	—
RL	...	< -40 dB	...
Internal memory	✓
Connector insertion loss	...	0.1 dB	...
Memory card slot	—
Power connectors type	<ul style="list-style-type: none"> • 230 V CEE 7/16 • 12 V - 2.1/5.5 mm Straight plug
Splice reuse	...	max. 5 times	...
Housing type	230 V Desktop

Main features	<ul style="list-style-type: none"> • Autonomous operation • 3000 indexed users, • 3000 indexed fingerprints (maximum 10 per user), • Non-volatile memory of recent 100 000 events and 150 000 presence records, • LCD display 2.8 ", 320 x 240 px - color, • Sound signaling, • Network interface: LAN, Wi-Fi, • Firmware upgrade via USB port, • The possibility of programming group or individual work schedules, taking into account the permissible time of lateness and earlier exit, • The distinction of standard events, overtime, lateness and earlier exits, • Data export to USB flash memory in "*.xls" format
Power supply	12 V DC / 1 A (power adapter included)
Weight	0.32 kg	...	0.83 kg
Dimensions	155 x 140 x 30 mm	...	160 x 80 x 80 mm
Operation temp	-10 °C ... 55 °C	-40 °C ... 75 °C	...
Permissible relative humidity	10 % ... 90 %
Manufacturer / Brand	Hikvision
SAP Code	302903580
Guarantee	3 years	2 years	2 years