




	ACCESS CONTROLLER PR311SE-BK ROGER	EXPANDER FOR CARD READERS INT-R SATEL
		
	108.17 EUR 108.17 EUR	81.73 EUR 81.73 EUR
Cards support	Unique EM 125kHz	...
Support	...	INTEGRA / CA-64
Reading distance of prox-keys	max. 15 cm	...
Number of supported devices	...	2
Keyboard built-in	—	...
Operation	...	Wiegand 26-66bit, DALLAS
Communication	<ul style="list-style-type: none"> • RS-485 • RACS (Roger) 	...
Selected features of the standalone mode	<ul style="list-style-type: none"> • 1000 indexed users • Operation with XM-2 I/O extension module (Full Standalone Mode) 	...
Current consumption	...	max. 150 mA
Main features	<ul style="list-style-type: none"> • The ability to add additional reader (bilateral way door control), • 3 programmable input lines NO/NC, • 2 programmable transistor outputs 1A, • One programmable relay output 1.5A/30V, • Door modes (Normal, Locked, Unlocked and Conditionally Unlocked), • Any topology of communication bus, • "Guest" type additional users support defined individually on each controller, • Integration with an alarm system via in/out line , 	<ul style="list-style-type: none"> • Tamper signaling • Capability to arm and disarm and clear alarm by using the readers • Capability to automatically unlock the door in case of fire alarm • Input for door unlocking with a button
Power supply	10 ... 15 V DC	12 V DC
Average current consumption	50 mA	...
Operation temp	-25 °C ... 60 °C	...
Permissible relative humidity	10 ... 95 % (non-condensing)	...
Weight	0.18 kg	0.08 kg

Dimensions	152.5 x 46 x 23 mm (Standard housing stand) 152.5 x 46 x 35 mm (Thicker housing stand)	140 x 68 mm
Manufacturer / Brand	ROGER	SATEL
Guarantee	3 years	2 years



DELTA-OPTI Monika Matysiak / VAT:PL5251295225 / 60-713 Poznań, ul. Graniczna 10
Tel:+48 61 864 69 60 / GSM:+48 607 60 11 66 / Fax:+48 61 864 69 65 / e-mail: info@delta.poznan.pl
Monday-Friday: 8.00-19.00 / Saturday: 8.00-14.00