



	SWITCH POE SPS-4P/1 5-PORT	INVERTER POWER GENERATOR F-3001/IS 2300 W FOGO
		
	42.15 GBP 42.15 GBP	703.92 GBP 703.92 GBP
LAN ports	5 x RJ45 (4 x PoE (802.3af))	...
Nominal power	...	2300 W
Maximum power	...	2500 W
Output voltage	...	230 V AC
Number of outlets	...	1 pcs - single-phase
Built-in voltmeter	...	—
Output frequency	...	50 Hz
Management	—	...
Voltage stabilization	...	Inverter (provides full voltage stabilization)
12V DC output	...	✓
Engine capacity	...	122 cm ³
LED diodes	Power, PoE, Gigabit Ethernet, Link/Act	...
Engine type	...	Rato R 120-Vi 1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine	...	Manual
Transmission speed	10 / 100 Mbps : 1 Port LAN + 4 LAN & PoE ports	...
Noise level during operation	...	89 dBA
Maximal output power	15.4 W / port PoE	...
Maximal total power	65 W	...
MAC addresses table	1k	...
Average fuel consumption	...	• 0.9 l/h - 50 % power • 1.5 l/h - 100 % power
Certificates	CE	...
Fuel tank capacity	...	4.5 l
Fuel gauge	...	✓
Power supply	52 V DC / 1.25 A (power adapter included)	...
Operation temp	-20 °C ... 70 °C	...

Main features	...	<ul style="list-style-type: none"> • Low oil level indicator light • Overload signaling • Overload protection • Battery charging possible • Save fuel by automatically reducing the revs as the load decreases • Possibility to combine two F-3001/IS power generators into one generator set
Color	...	Red
Weight	0.2 kg	24 kg
Dimensions	113 x 93 x 24 mm	520 x 320 x 460 mm
Manufacturer / Brand	...	FOGO
Guarantee	2 years	12 months