





	<a href="#">CHECKPOINT PK-2</a>	<a href="#">POWER GENERATOR F-3001 2700 W FOGO</a>	<a href="#">OVERVOLTAGE LIMITER AXON-POWER/DIN</a>
			
	6.24 EUR 6.24 EUR	542.32 EUR 542.32 EUR	25.05 EUR 25.05 EUR
Nominal power	...	2700 W	...
Support	PATROL-II-LCD	...	...
Output voltage	...	230 V AC	...
Rated voltage	...	...	230 V AC / 50 Hz
Main features	For indoor use	...	...
Number of outlets	...	2 pcs - single-phase	...
Maximal voltage	...	...	250 V AC / 50 Hz
Mount	Surface-mounted, Flush-mounted	...	...
Built-in voltmeter	...	—	...
Rated current	...	...	10 A
Operation range	3 ... 5 cm	...	...
Material	Plastic	...	...
Output frequency	...	50 Hz	...
Protection level Up L/PE, N/PE	...	...	≤ 1.3 kV
Voltage stabilization	...	—	...
Protection level Up L/N	...	...	≤ 3 kV
12V DC output	...	—	...
Engine power	...	5.6 HP	...
Nominal discharge current (L/N, L/PE, N/PE)	...	...	4 kA - 8/20 μs
Engine capacity	...	212 cm <sup>3</sup>	...
Maximum stroke current (L/N, L/PE, N/PE)	...	...	10 kA 8/20 μs (type 2)
Operation state indication	...	...	✓
Connectors type	...	...	2 x terminals
Engine type	...	Rato R210 1 cylinder, 4 stroke, gasoline, air cooled	...
Housing	...	...	• Plastic • DIN, TS-35 rail mounting
Starting the engine	...	Manual	...
Noise level during operation	...	96 dB	...
Average fuel consumption	...	1.4 l/h	...
Fuel tank capacity	...	3.6 l	...
Fuel gauge	...	✓	...

Weight	...	37 kg	0.075 kg
Dimensions	Ø 50 x 2.3 mm	580 x 395 x 405 mm	86 x 58 x 35 mm
Manufacturer / Brand	ROGER	FOGO	...
Guarantee	2 years	12 months	2 years



DELTA-OPTI Monika Matysiak / VAT:PL5251295225 / 60-713 Poznań, ul. Graniczna 10  
Tel:+48 61 864 69 60 / GSM:+48 607 60 11 66 / Fax:+48 61 864 69 65 / e-mail: info@delta.poznan.pl  
Monday-Friday: 8.00-19.00 / Saturday: 8.00-14.00