

Code: UT-132C

UNIVERSAL METER **UT-132C** UNI-T

Net: **17.68 USD** Gross: **17.68 USD**

UT-132C is a universal digital meter used to measure: voltage, current, resistance. The device also has a temperature measurement function.



SPECIFICATION

DC voltage measurement:	200 mV $\pm$ (0.5% + 2) @ 0.1 mV , 2 V $\pm$ (0.5% + 2) @ 1 mV , 20 V $\pm$ (0.5% + 2) @ 10 mV , 200 V $\pm$ (0.5% + 2) @ 100 mV , 600 V $\pm$ (0.8% + 2) @ 1 V
AC voltage measurement:	200 V $\pm$ (1.2% + 3) @ 0.1 mV : 45 Hz ... 400 Hz , 600 V $\pm$ (1.2% + 3) @ 1 mV : 45 Hz ... 400 Hz
DC current measurement:	2000 μ A $\pm$ (1% + 2) @ 1 μ A , 20 mA $\pm$ (1% + 2) @ 0.01 mA , 200 mA $\pm$ (1% + 2) @ 0.1 mA , 10 A $\pm$ (2% + 5) @ 0.01 A
AC current measurement:	—
Resistance measurement:	200 Ω $\pm$ (0.8% + 5) (not included) @ 0.1 Ω , 2 k Ω $\pm$ (0.8% + 5) @ 1 Ω , 20 k Ω $\pm$ (0.8% + 5) @ 10 Ω , 200 k Ω $\pm$ (0.8% + 5) @ 100 Ω , 2 M Ω $\pm$ (0.8% + 5) @ 1 k Ω , 20 M Ω $\pm$ (1% + 5) @ 10 k Ω
Capacitance measurement:	—
Inductance measurement:	—
Frequency measurement:	—
Square-wave signal duty ratio measurement:	—



Place for 9V battery:



Included, among others measuring adapter:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------