

Code: DY-3020/PRO

POWER GENERATOR **DY-3020/PRO** 2800 W Dynamo

Net: **397.74 EUR** Gross: **397.74 EUR**

A power generator with manual start is perfect for emergency power supply: a central heating furnace, home, office, camping, industrial equipment, as well as on boats and yachts. The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.

The generator is equipped with an Automatic Voltage Regulation system AVR, which allows to eliminate unfavorable voltage fluctuations to a large extent.

Attention! The device is not designed for continuous 24/7 operation. In case of long operation, the power generator should not be loaded with more than 75% of the nominal power.



SPECIFICATION

Nominal power:	2800 W
Maximum power:	3200 W
Output voltage:	230 V AC
Number of outlets:	2 pcs - single-phase
Built-in voltmeter:	✓
Output frequency:	50 Hz
Voltage stabilization:	AVR
Frequency measurement in Hz:	✓
Measuring the number of engine hours:	✓
12V DC output:	—
Alternator windings:	Copper
Engine power:	7 HP
Engine capacity:	208 cm ³
Engine type:	1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	92 dB
Average fuel consumption:	1.6 l/h
Fuel tank capacity:	15 l
Fuel gauge:	✓
Color:	Black

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Weight:	42.5 kg
Dimensions:	590 x 440 x 455 mm
Manufacturer / Brand:	Dynamo
Guarantee:	2 years

PRESENTATION



Front panel:



The display shows in sequence: voltage, frequency, number of engine hours:



Oil filler:



Choke lever and fuel valve:



The engine is started manually with a recoil starter:





Fuel filler and fuel gauge:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------