

Code: RXH-4K

RADIO CONTROLLER **RXH-4K** SATEL

Net: **39.24 EUR** Gross: **39.24 EUR**

The radio controller set provides a versatile solution for control of alarm systems, automatic opening gates or other devices. In addition to the relay outputs, controlled with key fobs, the receiver is equipped with additional signaling outputs. They can be used to indicate arming/disarming the alarm system, and to warn of low battery of the key fob. Because of the superheterodyne receiver with narrowband filtering, the RXH controllers provide superior range (up to 200 m) and high interference immunity.



SPECIFICATION

Radio communication range (at open area):	≤ 200 m
Number of controlled outputs:	4
Frequency range:	433.05 MHz ... 434.79 MHz
Support for up to 340 keyfobs:	Configuration possibility from PC
Adjustment range of changeover time in monostable mode:	1 s ... 255 s
Operation at bistable mode (on/off):	✓
Maximum current switched over by relay at DC 24V:	2 A
Current-carrying capacity of SS (OC) output:	500 mA
Current-carrying capacity of LV (OC) output:	50 mA
The KEELOQ code-hopping technology:	✓
Power supply:	12 V DC
Current consumption:	max. 100 mA
Permissible relative humidity:	≤ 93 %
Operation temp:	-10 °C ... 55 °C
Weight:	0.11 kg
Dimensions:	118 x 72 x 24 mm
Manufacturer / Brand:	SATEL
Guarantee:	2 years

PRESENTATION

View after remove the cover:



Mounting side view:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------