

Code: A-C18UV/5V

## ANTENNA AMPLIFIER A-C18UV/5V MEZON

Net: 5.39 EUR Gross: 5.39 EUR

The A-C18UV/5V antenna amplifier is designed to amplify weak signals of terrestrial TV.  
Warning! The amplifier is powered with 5 V.



### SPECIFICATION

|                           |                                   |
|---------------------------|-----------------------------------|
| Frequency range:          | 170 MHz ... 800 MHz               |
| Number of inputs/outputs: | 1 / 1                             |
| Input/output impedance:   | 75 $\Omega$                       |
| Connectors type:          | 1 x F plug / 1 x F socket         |
| Gain :                    | 18 dB                             |
| Self-noises:              | 4 dB                              |
| Max. output level:        | 94 dB $\mu$ V                     |
| DC voltage passing:       | ✓                                 |
| Main features:            | Built-in GSM / LTE filter         |
| Power supply:             | 5 V DC / 40 mA (from output side) |
| Operation temp:           | -10 °C ... 50 °C                  |
| Dimensions:               | Ø 21 x 47 mm                      |
| Manufacturer / Brand:     | MEZON                             |
| Guarantee:                | 2 years                           |

### PRESENTATION

Connectors view:



Side view:



## PACKAGE

|                                  |                    |
|----------------------------------|--------------------|
| Dimensions (L x W x H): 0x0x0 mm | Gross Weight: 0 kg |
|----------------------------------|--------------------|

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>  
 POL; 60-713 Poznań; Graniczna 10  
 e-mail: [delta-opti@delta.poznan.pl](mailto:delta-opti@delta.poznan.pl); tel: +(48) 61 864 69 60

