

Code: 12V/300MA/J-ESPE

SWITCHING ADAPTER 12V/300MA/J-ESPE

Net: 5.73 EUR Gross: 5.73 EUR

Attention! If the power adaptor is using for continuous work (24H) the rated current of the adaptor should be less than 80% of the maximal current.

Please pay attention for proper cooling conditions of the power adaptor during work!



SPECIFICATION

Model identifier:	12V/300MA/J-ESPE
Input voltage:	100 - 240 V AC
AC input frequency:	47 ... 63 Hz
Output voltage:	12.0 V DC
Output current:	0.3 A
Output power:	3.6 W
Average efficiency during work:	75.6 %
No-load power consumption:	0.1 W
Adapter type:	Switching
Output voltage adjustment:	—
Protections:	• Short-circuit • Overcurrent (overload) - automatic return to normal operation after the failure has ceased • Overvoltage
Number of outputs:	1 pcs
Power connectors type:	• 230 V Plug • 12 V : Jack 3.5 mm - Angular plug
Housing type:	Casing with plug
Length of the cable:	1.45 m
Weight:	0.06 kg
Dimensions:	60 x 39 x 64 mm
Guarantee:	2 years

PRESENTATION



DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Adapter's connector:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------



DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60