POWER DISTRIBUTION UNIT ACAR-ECO-PLUS (6 OUTLETS)

Net: 57.77 EUR Gross: 57.77 EUR

The new safety multi-outlet extension cord ACAR-ECO-PLUS enables save hundreds of kWh of electricity annually. Without any effort on your part, after swith off the main device (for example TV-set receiver connected to the "master" outlet) the ACAR-ECO-PLUS extension cord itself switch off the other devices connected to other outlets (for example: DVD player, Sat receiver, etc.), which can charge current in stand-by mode. It helps you to reduce electricity consumption in your home and environment protection.



SPECIFICATION

Maximal load power:	2300 W
Nominal voltage:	230 V AC / 50 Hz
Fuse:	10 A / 250 V
Switch:	two-way
Leak current:	< 0.5 mA
Response time:	< 25 ns
Nominal voltage of surge suppressor:	250 V
Protection level:	1.3 kV (L/N)
Nominal stroke current:	2 kA (L/N) - (8/20μs)
Maximum stroke current:	6.5 kA (L/N) - (8/20µs)
Electric shock protection system:	Ground connectors (pins) connected with ground wire of AC mains
Housing:	Plastic - non-flammable
Number of output outlets:	1 MASTER outlet, two-contact with ground contact 3 SLAVE outlets with auto switch off the power supply after switch off the receiver powered from MASTER outlet 2 outlets separate from MASTER outlet
Length of the cable:	1.45 m
Dimensions:	447 x 55 x 53 mm
Weight:	0.56 kg
Guarantee:	2 years

PRESENTATION

The extension cord has holders to arrange the cables:



DELTA-OPTI Monika Matysiak; https://www.delta.poznan.pl POL; 60-713 Poznań; Graniczna 10 e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

2024-05-04



RRRRRRRR

OUR OPINIONS



- o Electricity saving perfect solution.
- The automatic fuse allows to continuous work of the device without any breaks due to device overloads or short-circuits.

PACKAGE

Dimensions (L x W x H): 0x0x0 mm Gross Weight: 0 kg

2024-05-04 2/2