

Code: SVS-2-04

AMPLIFIER **SVS-2-04** 10 dB AXING

Linear amplifier for satellite and terrestrial digital television is used to amplify the signal after (*TV-SAT*) multiplexer or a single output to the subscriber from multiswitch. The device transmits the power supply and the 22 kHz signal.



Frequency range:	47 MHz ... 2400 MHz
Gain :	10 dB
Correction in satellite frequencies range:	—
Output level:	95 dBμV ... 97 dBμV
Connectors type:	"F"
DC voltage passing:	✓
Operation voltage:	14 ... 18 V DC
Current consumption:	≤ 40 mA (without LNB powering)
Manufacturer / Brand:	AXING
Guarantee:	2 years