

Code: FZK-011

THERMOSTAT **FZK-011**

The change-over thermostat can automatically switch power supply between connected devices when the temperature exceeds the set value.



Sensor type:	Bimetallic
Contact type:	• 1 x NC - opened after exceeding the set temperature, • 1 x NO - closed after exceeding the set temperature
Maximal power voltage:	250 V AC
Relay maximal load:	• 10 A - NC, • 5 A - NO
Temperature set range:	-20 °C ... 60 °C
Hysteresis:	7 °C ± 4 °C
Operation temp:	-20 °C ... 80 °C
"Index of Protection":	IP20
Assembly:	DIN TS-35 rail
Weight:	0.062 kg
Dimensions:	65 x 50 x 38 mm
Guarantee:	2 years