

Code: LE-402062

RESIDUAL CURRENT CIRCUIT BREAKER **LE-402062** THREE-PHASE, AC TYPE 30 mA 25 A LEGRAND

Residual current circuit breaker with rated sensitivity of $I_{\Delta n} = 30\text{mA}$, AC type. The LE-402062 circuit breaker is compatible to DIN TS-35 rail mounting system.



Device type:	Residual current circuit breaker, Three-phase, AC type
Rated sensitivity:	30 mA
Rated current:	25 A
Number of poles:	4
Breaking capacity:	10000 A
Rated voltage:	400 V AC / 50 Hz
Connectors type:	screw terminals
Housing:	Plastic, DIN, TS-35 rail mounting
Width in 17.5 mm modules:	4
Weight:	0.312 kg
Dimensions:	71 x 83 x 75 mm
Manufacturer / Brand:	LEGRAND
Guarantee:	2 years