

Code: INT-KLFR-B

KEYPAD FOR ALARM CONTROL PANEL **INT-KLFR-B** SATEL

The INT-KLFR-B keypad is intended for daily operations and programming the Integra series alarm control system.

The built-in proximity card reader allows to operate the system without the necessity to remember passwords. With the LCD display showing text messages, even advanced functionalities of the alarm control unit are simple and convenient.



Support:	INTEGRA
Main features:	• Large, easily readable LCD with backlight displaying detailed information on system state • 3EOL configurations support - 2 Inputs • Operation status LED indicator • Alarms: keypad hold-down PANIC, FIRE and AUX • Buzzer for acoustic signaling of some system events • RS-232 port allows to programming using the PC with GUARDX software installed • proximity reader built-in - Unique EM 125kHz • Microswitch as tamper contact
Power supply:	12 V DC
Current consumption:	max. 110 mA
Color:	Black
Operation temp:	-10 °C ... 55 °C
Weight:	0.34 kg
Dimensions:	145 x 143 x 25 mm
Manufacturer / Brand:	SATEL



DATA SHEET

Guarantee:

2 years