

Code: UT-131D

UNIVERSAL METER **UT-131D** UNI-T



The UT-131D is a universal digital meter used to measure: voltage, current, resistance, diodes.

DC voltage measurement:	200 mV $\pm$ (0.7% + 3) @ 0.1 mV , 2000 mV $\pm$ (0.5% + 2) @ 1 mV , 20 V $\pm$ (0.7% + 3) @ 0.01 V , 200 V $\pm$ (0.7% + 3) @ 0.1 V , 250 V $\pm$ (0.7% + 3) @ 1 V
AC voltage measurement:	200 V $\pm$ (1.2% + 3) @ 0.1 V , 250 V $\pm$ (1.2% + 3) @ 1 V
DC current measurement:	2000 μ A $\pm$ (1.0% + 2) @ 1 μ A , 20 mA $\pm$ (1.0% + 2) @ 0.01 mA , 200 mA $\pm$ (1.0% + 2) @ 0.1 mA , 10 A $\pm$ (1.2% + 5) @ 0.01 A
AC current measurement:	—
Resistance measurement:	200 Ω $\pm$ (1.0% + 2) @ 0.1 Ω , 2 k Ω $\pm$ (0.8% + 2) @ 0.001 k Ω , 20 k Ω $\pm$ (0.8% + 2) @ 0.01 k Ω , 200 k Ω $\pm$ (0.8% + 2) @ 0.1 k Ω , 20 M Ω $\pm$ (1.2% + 3) @ 0.01 M Ω , 200 M Ω $\pm$ (5.0% + 10) @ 0.1 M Ω
Capacitance measurement:	—
Inductance measurement:	—

Frequency measurement:	—
Temperature measurement:	—
Automatic change of measuring ranges:	—
hFE:	—
Diode test:	✓
Sound signal of the continuity test:	✓
Checking TTL logic states:	—
RS-232:	—
Main features:	• NCV - electric field detection function • Large, readable LCD display with backlight • Hold - stopping the meter reading • Low battery indicator • Aesthetic and solid construction
Power supply:	2 x 1.5V, type AAA/LR03 battery - included
Weight:	0.21 kg
Dimensions:	134 x 77 x 47 mm
Manufacturer / Brand:	UNI-T
Guarantee:	2 years