

Code: MHD-002P

MODULATOR DVB-T **MHD-002P** TERRA

The MHD-002P digital modulator allows to put the HD signal (from camera, terrestrial, satellite TV receiver, Blu-ray, DVD player, etc.) from HDMI input to RF OUT output as DVB-T (COFDM), Full HD 1080p standard in VHF/UHF bands.

The device has an HDMI input and output that allow you to view the image from the connected signal source.



Inputs:	<ul style="list-style-type: none"> • 1 pcs HDMI, Full HD 1080p • 1 pcs RF (F)
Output:	<ul style="list-style-type: none"> • 1 pcs RF (F) • 1 pcs HDMI
Encoding:	MPEG-4 AVC / H.264
Supported HDMI resolutions:	480i, 480p, 576i, 576p, 720p, 1080i, 1080p @ 24 / 50 / 60 fps
RF output level adjustment:	60 dB μ V ... 90 dB μ V
RF output frequency (channels) range:	174 ... 230 MHz ; 470 ... 862 MHz
Modulation type:	64-QAM
Power supply:	12 V DC / 1 A (power adapter included)
Main features:	<ul style="list-style-type: none"> • The channel selection is made using the buttons • The built-in display shows the currently used channel • Adjusting the signal level at the output : 0 ... 30 dB • The device has an HDMI input and output that allow you to view the image from the connected signal source
Weight:	0.17 kg
Dimensions:	133 x 63 x 39 mm
Manufacturer / Brand:	TERRA
Guarantee:	2 years