

Code: ATLO-WB2-TUYA

DUAL SMART LIGHT SWITCH **ATLO-WB2-TUYA** Wi-Fi, Tuya Smart

The ATLO-WB2-TUYA switch allows you to turn the lighting on and off wirelessly via the application or by pressing a button. For proper functioning of the device, it is necessary to connect it to the Wi-Fi network with Internet access.

Beyond direct control, the device has the ability to program the on and off schedule and linking to different system events. It is possible to create action scenarios with other devices. Voice control allows you to control the device via voice commands from Amazon Alexa or the Google Assistant (Internet access required).

Tuya is an international home automation platform that connects thousands of products made by different manufacturers. The system can support all the most popular communication protocols such as Wi-Fi, Zigbee, Bluetooth.

Attention! Controlling the device and schedule settings is possible if the device has access to the Internet. The product can only be paired with a 2.4 GHz WiFi router.

Attention! A neutral wire to the switch is required for proper operation.



Application:	Works with lighting - switching on/off
Rated voltage:	100 ... 240 V AC, 50 / 60 Hz
Maximum power:	300 W (for each output)
Rated current:	max. 10 A
Number of buttons:	2
Number of outputs:	2
Connector type:	screw terminals
Wireless:	Wi-Fi, 2.4 GHz - IEEE 802.11 b/g/n
Mobile phones support:	<ul style="list-style-type: none"> The Tuya Smart free application on Android The Tuya Smart free application on iOS
Main features:	<ul style="list-style-type: none"> Local control by physical button, schedule, timer, Setting scenarios by different events, remote access, voice control, LED indication



DATA SHEET

Housing:	Plastic
Color:	White
Operation temp:	-20 °C ... 50 °C
Permissible relative humidity:	≤ 80 %
Weight:	0.098 kg
Dimensions:	87 x 86 x 41 mm
Guarantee:	2 years