

Code: ATLO-LWB2-TUYA

ELECTRIC ENERGY MONITOR **ATLO-LWB2-TUYA** ONE-PHASE TWO-CHANNEL

Single-phase electric energy monitor. This monitor performs semi-direct measurement which makes it suitable for use in both lighting and socket circuits of considerable power.



Support:	Tuya Smart
Device type:	Electric Energy Monitor, One-phase two-channel
Wireless:	Wi-Fi, 2.4 GHz - IEEE 802.11 b/g/n + Bluetooth LE
Rated voltage:	230 V AC, 50 / 60 Hz
Measurement method:	Semi-indirect measurement using an current transformer - 2 pcs included
Current:	2 x 80 A - Max. current
Connectors type:	screw terminals
Mobile phones support:	It is possible to operate via the Wi-Fi network from the mobile application on the iOS, Android systems : • The Tuya Smart free application on Android • The Tuya Smart free application on iOS
Measured parameters:	• Voltage • Current • Power consumption
Housing:	Plastic
Operation temp:	-10 °C ... 40 °C
Weight:	0.13 kg
Dimensions:	44 x 39 x 22 mm
Manufacturer / Brand:	ATLO
Guarantee:	2 years